









Doc no: TE-NT-SP-0001 Revision: 1.00	Specification Document	Broadband Infracore 
---	-----------------------------------	---

**TITLE: Technical Requirement Specification: Energy storage device
and their security measures**

Unique Identifier:	TE-NT-SP-0001
Document Type:	Specification
Revision:	1.00
Effective date:	March 2021
Total pages:	21
Revision Date:	February 2021
Next Revision Date:	February 2022
Information Security Level:	Normal

	Name	Signature	Date
Drafted by:	Senior Engineer – Willem Grobbelaar Engineer in Training: Teteki Maloka Senior Specialist: Andre van der Westhuizen	 	2021-07-30 30 / 07 / 2021 2021-07-30
Reviewed by:	Senior Specialist: Service Order Delivery & Network Performance - Howard Mahlangu		01-09-2021
Reviewed by:	Senior Specialist: Facilities, Quality & Compliance - Thamsanqa Qwabe		04-Aug-21
Reviewed by:	Manager: Northern Region (Johannesburg) - Moletse Mabitle		30/07/2021
Supported by:	Chief Engineer – Potsane Malebanye (Pr Eng.)		01/09/2021
Recommended	DRC Chair – Hamilton van Tonder		14/09/2021
Approved by:	Chief Technical Officer – Gift Zowa		18/09/2021



Doc no: TE-NT-SP-0001 Revision: 1.00	Specification Document	<i>Broadband Infracore</i> 
---	-----------------------------------	---

TABLE OF CONTENTS

TABLE OF CONTENTS	2
1. SCOPE	4
2. REFERENCE DOCUMENTATION (LATEST VERSIONS)	4
3. DEFINITIONS, ABBREVIATIONS AND ACRONYMS	4
3.1 Definitions	4
3.2 Abbreviations	5
3.3 Acronyms	5
4. ENERGY STORAGE DEVICE	5
4.1 Design Life	6
4.2 Cycle Life	6
4.3 Shelf Life	6
4.4 Rating and Nominal Voltage	6
4.5 Physical Size	6
4.6 Weight	7
4.7 Recharging	7
4.8 Float Charging	7
4.9 Operating Voltage	7
4.10 Parallel Operation	7
4.11 Protection	7
4.12 Operating Temperature	7
4.13 Electromagnetic compatibility (EMC) and Safety	8
4.14 DC Power Connections	8
4.15 Controller (not applicable to VRLA Batteries)	8
4.16 Tracking and Tracing of Energy Storage Devices	9
4.17 Maintenance	10
4.18 System Failure Rate and other references	10
4.19 Materials and Components	10
4.20 Brochures	10
4.21 Installation Energy Storage Devices on behalf of Broadband Infracore	10
4.22 Warranty	11
5. SECURITY MEASURES	11
5.1 Retrofitted battery security	11
5.2 Indoor and outdoor installations	12
5.2.1 New Indoor Installations	12

Doc no: TE-NT-SP-0001 Revision: 1.00	Specification Document	<i>Broadband Infracore</i> 
---	-----------------------------------	---

5.2.2 Outdoor installations.....	12
5.3 Brochures	13
6. APPENDICES.....	14
6.1 Appendix A: Maintenance Processes.....	14
6.2 Appendix B: Support Processes.....	14
6.3 Appendix C: Schedule of Compliance / Non-compliance / Information	14
APPENDIX A: MAINTENANCE PROCESSES	15
APPENDIX B: SUPPORT PROCESSES	16
APPENDIX C: SCHEDULE OF COMPLIANCE / NON-COMPLIANCE / INFORMATION	17

Doc no: TE-NT-SP-0001 Revision: 1.00	Specification Document	
---	-----------------------------------	--

1. SCOPE

The scope of this specification is for Energy storage devices and security measures (new and retrofit) to limit theft and safe keeping of energy storage devices installed at various Broadband Infracore sites across South Africa.

Energy storage devices may include traditional Valve Regulated Lead Acid (VRLA) technologies as well as newer technologies which are safe, efficient and effective.

The security measures describe the standards of the physical properties and safeguarding of Energy storage devices installed at Broadband Infracore sites.

These measures are to be implemented as follows:

- Retro-fitted to existing infrastructure; and
- Indoor and out-door installations.

2. REFERENCE DOCUMENTATION (LATEST VERSIONS)

- SANS 1042-1 – Wiring of premises.
- SABS IEC 60950- Safety of information technology equipment, including electrical business equipment (Alternative UL950).
- SANS 529 Degrees of protection provided by enclosures.
- EN61000-4-2 Electromagnetic compatibility (EMC) - Part 4-2: Testing and measurement techniques - Electrostatic discharge immunity test.
- EN61000-4-3 Electromagnetic compatibility (EMC)- Part 4-3: Testing and measurement techniques- Radiated, radio-frequency, electromagnetic field immunity test.
- EN 55032 Electromagnetic compatibility of multimedia equipment - Emission requirements.
- EN 55024 Information technology equipment - Immunity characteristics - Limits and methods of measurement.
- SANS 949: 2005 Strong room and safe doors.

3. DEFINITIONS, ABBREVIATIONS AND ACRONYMS

3.1 Definitions

Word	Meaning
C2, C4, C10 rate	Capacity of the battery at the various discharge rates i.e. 2 hours, 4 hours or 10 hours respectively.
Float charge	Float voltage is the voltage at which the device is maintained after being fully charged to maintain that capacity by compensating for self-discharge of the device.
Shelf life	Shelf life is the life of the module (in years) from the date it is manufactured

Word	Meaning
	to the date it is first installed and commissioned.

3.2 Abbreviations

Abbreviation	Description
A	Ampere
AC	Alternating Current
Ah	Ampere-hour
DC	Direct Current
DoD	Depth of Discharge
e.g.	exempli gratiā, meaning “for example”
mm	millimetre
RMS	Root Mean square
V	Volt
W	Watts

3.3 Acronyms

Acronym	Description
ETS	European Telecommunication Standard
EMC	Electromagnetic compatibility
IEC	International Electro-technical Commission
LVD	Low Voltage Disconnect
MTBF	Mean time between failure
OHSACT	Occupational Health and Safety Act
PDF	Portable Document Format
QA	Quality Assurance
SABS	South African Bureau Standard
SANS	South African National Standard
SNMP	Simple Network Management Protocol
VRLA	Valve Regulated Lead Acid

4. ENERGY STORAGE DEVICE

Broadband Infraco intends to install existing installed technologies (VRLA) and newer technology storage devices with front terminal at Broadband Infraco sites.

The same Energy storage device shall be capable of being used in all different rectifiers systems deployed by Broadband Infracore in various configuration, by increasing parallel multiple devices where extra storage capacity is required.

In all cases, rectifier systems will be equipped with at least 2 x Energy storage devices as described in this specification, but in most cases, 8 devices will be put in parallel up to a maximum estimated 12 units.

4.1 Design Life

Each storage device shall have a design life of at least 18 Years.

4.2 Cycle Life

Each storage device shall have a minimum cycle capability of at least 2 500 cycles at 40%. Depth of Discharge (DoD).

Performances of different DoD rates should be supplied with submission.

4.3 Shelf Life

Each storage device shall have a shelf life of at least 2 Years at an uncontrolled temperature location without putting them on charge and still be able to utilise the energy storage device with no degradation of any performances after this period has lapsed and the device being installed the first time.

4.4 Rating and Nominal Voltage

Energy storage devices should have a nominal voltage of 48V. Energy storage devices may have a nominal voltage of only 12V on condition that 4 devices can be put in series to form a 48V string.

Each storage device (or string of devices) shall have a capacity of the following typical capacities at 48V DC:

- a) $\geq 100\text{Ah}$;
- b) $\geq 150\text{Ah}$; and
- c) $\geq 200\text{Ah}$.

4.5 Physical Size

The 48V Energy storage device (or string of 4 x 12V devices) should not exceed the following dimensions:

- a) Height – 330mm (current standard battery shelf height deployed in Broadband Infracore);
- b) Width – 550mm (to be fitted in a standard 600mmx 600mm cabinet); and
- c) Depth – 550mm (to be fitted in a standard 600mmx 600mm cabinet).

Doc no: TE-NT-SP-0001 Revision: 1.00	Specification Document	
---	-----------------------------------	--

4.6 Weight

Each 48V storage device shall not weigh more than 80kg.

4.7 Recharging

Each storage device shall be able to be fully charged from 0 - 95% stage of charge in the following time periods and must be user definable:

- a) In less than 1 hour; and
- b) Over a period of 24 hours (default setting).

Recharge graphs at different recharge rates to be supplied with submission.

4.8 Float Charging

Each 48V storage device (or string of 4 x 12V devices) shall be able to be charged/float at a continuous basis for the duration of its life at a DC voltage of 53V-54.5V at 25°C (positive earth).

4.9 Operating Voltage

During failing of AC powers to the rectifiers, DC voltage of the device is expected to decrease gradually. Each storage device shall be able to be fully operational under a voltage range of between 54.5V-42V.

Discharge graphs at different discharge rates to be supplied with submission.

4.10 Parallel Operation

Each storage device shall be able to be connected in parallel with the same units up to a total of not less than 12 of the exact same devices.

4.11 Protection


The device (excluding VRLA battery type) shall in all aspects be able to withstand the circumstances, without any damages, where the following fault condition for a duration of time has occurred. The device shall return to normal after the fault has cleared.

- a) Over charge (voltage and current);
- b) Over discharge;
- c) Reverse polarity;
- d) Over temperature; and
- e) Cell imbalance (in the scenario of individual cells).

4.12 Operating Temperature

- a) The device should be designed to operate in temperature range from 0°C up to 55°C.

Performance degradation may be applicable and the suppliers to provide the temperature response graphs.

<p>Doc no: TE-NT-SP-0001</p> <p>Revision: 1.00</p>	<p>Specification Document</p>	<p>Broadband Infracore</p> 
--	--	--

4.13 Electromagnetic compatibility (EMC) and Safety

The energy storage shall comply with the following EMC requirements:

- a) EN 55032;
- b) EN 6100-4-2;
- c) EN55024; and
- d) and carry the equivalent's CE mark.

A compliance certificate and or proof shall be provided.

4.14 DC Power Connections

Each energy storage device shall be able to be connected to a rectifier with at least 1 x 50mm² red cable to the positive terminal and 1 x 50mm² blue cable to the negative terminal.

4.15 Controller (not applicable to VRLA Batteries)

Each storage device shall have a built-in controller for effective cell balancing, system control and charging algorithms.


4.15.1 Controller Display and Interfaces and Alarms

- a) Each controller should have preferably a backlit LCD/LED readout with the following comprehensive current conditions including the following must be available on the display:
 - i. DC Voltage;
 - ii. DC Current;
 - iii. Temperature.
- b) The controller should provide indicative device conditions, simplifying fault diagnostics as far as possible, where the device behaves in a manner less than ideal. There should be at least the following indication on the controller self.
 - i. Unit disconnected/faulty;
 - ii. Reverse polarity;
 - iii. Under/Over Voltage;
 - iv. Over current charge/discharge; and
 - v. Over temperature.
- c) In the scenario that the controller is removable, the system must continue to be functional even when the controller is removed.

4.15.2 Software

The Energy storage devices must be supplied with a suitable client PC software for monitoring and managing the operation of the device. This section describes the operation of the software.

The software must also have a web base application, android compatible, to allow for remote reconfiguration.

<p>Doc no: TE-NT-SP-0001</p> <p>Revision: 1.00</p>	<p>Specification Document</p>	<p>Broadband Infracore</p> 
--	--	--

4.15.2.1 Communication

The controller must have the following communication interfaces to facilitate system interrogation:

- a) USB and/or 10BaseT Ethernet/serial Console for local and remote system configuration and management;
- b) The controller module must be able to support Simple Network Management Protocol (SNMP).

4.15.2.2 Password Protection

Access to the device via the software should be password protected.


4.15.2.3 Built-in Anti- Theft Feature

- a) During initial commissioning/connection to DC power, the energy storage device should be password protected and can only be operated by authorized personnel (and OEM in scenario that password is forgotten by operator) with a valid password. The password should be loaded to the device via the PC.
- b) If the energy storage device is disconnected from the DC power source, an anti-theft feature must be standard and built in each device which requires the password to be loaded to restart the device. In the event of disconnection from the DC power source, to restart the device, a PC should be required to be connected to the energy storage device with the required password.
- c) If the device disconnects due to a safety event (as indicated here below), it automatically reconnects once the safety event is over and should not activate an anti-theft feature.
 - i. Over- and under voltage cut off;
 - ii. Over-current cut off;
 - iii. Over temperature cut off.

4.15.2.4 Management and logging function

- a) The Energy Storage Device should have proper monitoring and algorithm built-in to ensure effective, efficient and smooth operation of the devices over the life of the device.
- b) The controller shall log and store all events and data logs up to 5000 entries (i.e. including but not limited to alarms, general operating conditions, voltage and currents. All logs should include the time, date and condition of event and data. When the logs entry is full, the oldest log event will be deleted first to capture the latest log event
- c) All logs shall be able to be retrieve and be exported to Excel via a PC.

4.16 Tracking and Tracing of Energy Storage Devices

<p>Doc no: TE-NT-SP-0001</p> <p>Revision: 1.00</p>	<p>Specification Document</p>	<p><i>Broadband Infraco</i> </p>
--	--	--

Over and above the physical Energy storage devices and protection mechanisms stipulated within this specification, a digital solution for tracking and tracing stolen Energy storage devices should be provided with full specification of its operability and any required ancillary support systems.

4.17 Maintenance

The device should preferably not require any periodic maintenance. In the case of any maintenance are required, details of the maintenance tasks and the frequency shall be clearly indicated.

4.18 System Failure Rate and other references

- a) The energy storage system design MTBF in operating hours should be stated.
- b) References of other users/operators utilizing the same system/building blocks and field reports (of minimum 3 years) indicating the number of devices supplied, and the achieved failure rate shall be provided with the submission.

4.19 Materials and Components


All materials and components shall be new and shall not have been in prior service except as required during factory testing and commissioning.

4.20 Brochures

- a) Broadband Infraco shall be provided with a full set of brochures of the energy storage devices, all performance- and datasheets, management and software indicating the detail specification of the various products offered.
- b) Broadband Infraco shall be provided with a full set of operation, fault finding and installations manuals.

4.21 Installation Energy Storage Devices on behalf of Broadband Infraco

- a) It shall be expected from the supplier of the Energy Storage Devices to supply, deliver and install the equipment in a relevant container and or datacentre on behalf of Broadband Infraco on request.
- b) Installation of new Energy Storage Devices on site where existing batteries needs to be replaced, the supplier:
 - i. Shall supply, transport and install the new energy storage devices on request;
 - ii. The installer shall replace the old batteries with the new Energy Storage system during a “live” cut-over without disconnecting any circuit or power;

<p>Doc no: TE-NT-SP-0001</p> <p>Revision: 1.00</p>	<p>Specification Document</p>	<p>Broadband Infracore </p>
--	--	---

- iii. Shall recover the old equipment and safely dispose of the old batteries, complying with all the applicable legislation and OHSACT requirements;
- iv. Shall issue the relevant certificate of compliance and test report as per SANS 10142-1.

4.22 Warranty

In the event of any of the following items/components becoming defective, the supplier shall replace such defective item, free of charge, with a minimum of 5 years but preferably more, from the date of installation.


5. SECURITY MEASURES

- a) Broadband Infracore will make use of security measures to safeguard energy storage devices at PoP sites where theft is prevalent.
- b) A pilot test on selected sites is required where the installation of batteries, cabinets solution will be done.
- c) The intention is to trial the solution on these selected pilot sites, with the objective of nationwide roll out if required.
- d) The measures will be based on two approach methods:
 - i. Retro fitted – This is where there is an existing site where security measures are implemented by fitting security measures on existing energy storage devices. The fitment process must not require service interruptions to achieve the required results;
 - ii. Indoor and outdoor installations – This is where a new site is built or where energy storage devices are moved to an outside facility to house the energy storage devices.
- e) The energy storage devices security measures must comply with the following standards indicated below:

SANS 949:2005 - Strong room and safe doors

 - Category 2ADM that withstands break in with:
 - Hand tools for 1 hour;
 - Drilling for 1 hour;
 - Angle grinder for 1 hour.
 - Category 3 that withstands break in with:
 - Hand tools for 1 hour;
 - Drilling for 1 hour;
 - Angle grinder for 1 hour;
 - Oxy Acetylene cutting for 1 hour.

5.1 Retrofitted battery security

<p>Doc no: TE-NT-SP-0001</p> <p>Revision: 1.00</p>	<p>Specification Document</p>	<p>Broadband Infracore</p> 
--	--	--

The retrofitted security measures must comply to Category 2AMD of the SANS standard.

In addition to this, the properties of the security measures must comply to the following two options:

Option 1:

- i. Must be implementable without any down time of the site;
- ii. Replacement of Energy storage device must be possible e.g. no irreversible and permanent fixture of the Energy storage device or make replacement impossible or difficult;
- iii. Replacement of individual Energy storage device must be possible;
- iv. Must be compatible with any OEM manufacturer equipment;
- v. Must be obtainable as an off the shelf item, at least for battery replacement and
- vi. Must be approved by the OEM battery supplier.

Option 2: Epoxy Compound Specifications:

- i. The batteries to be stored in an anti-theft cabinet or vault and be fixed to the cabinet by means of Epoxy compound solution;
- ii. The solution must be non-breakable once it has set;
- iii. The solution must not be harmful to the environment and should not emit toxic gases;
- iv. The solution must be safe for humans;
- v. The solution must be non-flammable and non-explosive;
- vi. The solution must be non-soluble if mixed with commonly existing chemicals.


5.2 Indoor and outdoor installations

As mentioned before in this document, this type of installation will be used in new sites.

5.2.1 New Indoor Installations

- a) The security measures must comply to Category 2AMD of the SANS standard.
- b) In addition to this, the properties of the security measures must comply with the requirements of retrofitted installations.

5.2.2 Outdoor installations

Doc no: TE-NT-SP-0001 Revision: 1.00	Specification Document	<i>Broadband Infracore</i> 
---	-----------------------------------	---

- a) The security measures must comply to Category 3 of the SANS standard.
- b) In addition to this the security measure must comply with the following:
 - i. The security measure must be a cabinet/vault type enclosure;
 - ii. The cabinet/vault must be able to house a rectifier system with up to 4 x 48V energy storage device strings in parallel;
 - iii. The cabinet/vault type enclosure must be constructed of steel.
 - iv. The cabinet/vault must have fan cooling but must also be capable to house an air conditioning system when required;
 - v. The door must be lockable with a standard Broadband Infracore padlock or lock barrel;
 - vi. A remote (via NOC) locking system is also preferred but must have a fail-safe function in case of a power failure so that access is always possible;
 - vii. The cabinet/vault must be mountable on a concrete plinth so that it cannot be lifted to gain access to the cabinet/safe;
 - viii. The cable access to the equipment container must be underground in a 110mm duct;
 - ix. The duct must be protected with concrete encasement of at least 250mm deep;
 - x. In addition to the above requirements as an extra safety measure, the option must be available for batteries to be fixed to the cabinet by means of Epoxy compound solution compliant to paragraph 5.1 Option 2.

5.3 Brochures

Broadband Infracore shall be provided with brochures, datasheets, pictures of the proposed security measure of all the various products offered for retrofit as well as indoor and outdoor products.

<p>Doc no: TE-NT-SP-0001</p> <p>Revision: 1.00</p>	<p>Specification Document</p>	<p>Broadband Infraco </p>
--	--	---

6. APPENDICES

Selected schedule(s) are found in the appendices and forms part of this specification.

6.1 Appendix A: Maintenance Processes

Suppliers are required to respond to all questions in this schedule.

Broadband Infraco will make use of the information provided during its price evaluation process to assess the complete lifecycle cost of the proposed systems, as well as the potential impact on the total cost of ownership of the equipment over a period of 10 years and 30 years.

6.2 Appendix B: Support Processes

Suppliers are required to respond to all questions in this schedule.

Broadband Infraco will make use of the information provided during its technical evaluation process to assess whether a supplier's support processes will be able to effectively support Broadband Infraco's requirements.

6.3 Appendix C: Schedule of Compliance / Non-compliance / Information

Suppliers are required to complete this schedule and must take note of the following:


1. A detailed statement of compliance or non-compliance, accompanied by reasons (if any) for every requirement called for in the specification, must be submitted. The detailed statements must be in the format as provided in Schedule A. Where needed, further notes may also be appended to the schedule;
2. It must be clearly stated whether the equipment offered, for each of the specified requirements, is:
 - **Fully Compliant;** or
 - **Non-compliant.**
3. Phrases such as "**noted**" must only be used against paragraphs that are for information only and carry no contractual commitment.
4. Phrases such as "**noting**", "**will comply**" and "**comply, except**", in a paragraph that requires a compliance or non-compliance statement will be read as non-compliance.
5. The letter appended at the end of each paragraph in the specification requires the following type of response.

END

<p>Doc no: TE-NT-SP-0001</p> <p>Revision: 1.00</p>	<p>Specification Document</p>	<p>Broadband Infracore</p> 
--	--	--

APPENDIX A: MAINTENANCE PROCESSES

1. What routine maintenance procedures are required for the energy storage device (if any) components of the proposed system solutions:
 - a) How often is routine maintenance required (if any)?
 - b) Explain what tasks should typically be performed during routine maintenance and what tools and or training will be expected of such personnel?
2. Provide a life cycle costing model/analysis taking into account all factors/relevant assumptions predicting the life expectancy of the supplied solution for energy storage device individually operating under normal circumstance. Normal circumstance is regarded as 1 cycle per month with a depth of discharge of 80% at average ambient temperature of 22 degrees Celsius. A predicted total cost to company including all aspects over a 10 and 30 year life cycle is to be calculated and supplied.
3. The supplied shall give a technology life cycle positioning of the equipment offered which shall include but not limited to the following:
 - a) When was the offered equipment first introduced into the commercial market?
 - b) When was the last upgrade and when is the next planned upgrade?
 - c) What is the life expectancy of the offered equipment before equipment will become obsolescent and obsolete?


<p>Doc no: TE-NT-SP-0001</p> <p>Revision: 1.00</p>	<p>Specification Document</p>	<p>Broadband Infracore</p> 
--	--	--

APPENDIX B: SUPPORT PROCESSES


1. Support services
 - a) Do you offer support services beyond the sale of equipment?
 - b) If so, how are such support services provided inside and outside the equipment warrantee period?
 - c) If support services are offered, are there additional cost implications?
 - d) If there are additional cost implications, kindly provide a detailed breakdown of these costs?
2. How will Level 2 and Level 3 support queries be handled? Please describe the process that would be followed for each support level. As part of the process descriptions, kindly make reference to the following aspects:
 - a) Who will be responsible for handling Level 2 and Level 3 support queries?
 - b) Access to Level 3 support engineers:
 - c) Availability of local subject-matter experts.
3. Repair of faulty equipment
 - a) How will in-warranty and out-of-warranty repairs be handled? What is the process to be followed for each and what turnaround times can be expected?
 - b) Will spares be kept inside the country?
 - c) Will repairs be done inside the country?
 - d) Will modules / equipment / energy storage devices be readily available for swop-out during failures?
4. Training
 - a) What training is offered on purchase, and what is offered on an ongoing basis?
 - b) Will training be conducted inside the country or outside of the country?
 - c) What training is offered / required in terms of continuous certification of staff and contractors?
 - d) Is an online help / training facility available?
 - e) Is a “train the trainer” concept supported whereby experts are created locally?
5. If applicable, please describe how firmware / software upgrades are handled, including licensing issues, etc.
6. Supplier to provide an end of life management, which include the disposal process.

APPENDIX C: SCHEDULE OF COMPLIANCE / NON-COMPLIANCE / INFORMATION


Specification		
Specification	Fully Compliant / Non-compliant / Noted	Comments (if applicable)
4 Energy Storage device		
4.1 Design life		
4.2 Cycle Life		
4.3 Shelf life		
4.4 Rating and nominal voltage		
4.4.a		
4.4.b		
4.4.c		
4.5 Physical Sizes		
a		
b		
c		
4.6 Weight		
4.7 Recharging		
a		
b		
4.8 Float charging		
4.9 Operating Voltage		
4.10 Parallel Operation		
4.11 Protection		
a		
b		
c		
d		
e		
4.12 Operating temperature		
a		
b		
4.13 EMC and Safety		

Doc no: TE-NT-SP-0001 Revision: 1.00	Specification Document	Broadband Infracore 
---	-----------------------------------	---

a		
b		
c		
d		
4.14 DC Power connections		
4.15 Controller (not applicable to VRLA batteries)		
4.15.1 Controller display and interfaces and alarms		
a		
a.i		
a.ii		
a.iii		
b.i		
b.ii		
b.iii		
b.iv		
b.v		
c		
4.15.2 Software		
4.15.2.1 Communication		
4.15.2.1.a		
4.15.2.1.b		
4.15.2.2 Password Protection		
4.15.2.3 Built-in Anti-theft feature		
4.15.2.3a		
4.15.2.3b		
4.15.2.3.c.i		
4.15.2.3.c.ii		
4.15.2.3.c.iii		
4.15.2.4 Management and logging function		
4.15.2.4.a		
4.15.2.4.b		
4.15.2.4.c		
4.16 Tracking and Tracing of Energy storage		

Doc no: TE-NT-SP-0001 Revision: 1.00	Specification Document	Broadband Infracore 
---	-----------------------------------	--

devices		
4.17 Maintenance		
4.18 System Failure Rate and other references		
4.18.a		
4.18.b		
4.19 Materials and components		
4.20 Brochures		
4.20.a		
4.20.b		
4.21 Installation Energy Storage Devices on behalf of Broadband Infracore		
4.21.a		
4.21.b		
4.21.b.i		
4.21.b.ii		
4.21.b.iii		
4.21.b.iv		
4.22 Warranty		
5 Securities measures		
a		
b		
c		
5.1 Retrofitted energy storage devices security		
Option 1		
i		
ii		
iii		
iv		
v		
vi		
Option 2		
i		
ii		
iii		
iv		
v		

Doc no: TE-NT-SP-0001 Revision: 1.00	Specification Document	<i>Broadband</i> Infracore 
---	-----------------------------------	--

vi		
5.2 Indoor and outdoor installations		
5.2.1 New Indoor Installations		
a		
b		
5.2.2 Outdoor installations		
a		
b		
b.i		
b.ii		
b.ii		
b.iv		
b.v		
b.vi		
b.vii		
b.viii		
b.ix		
b.x		
5.3 Brochure		

