


	GENERATION COAL FIRED STATIONS OHS SPECIFICATION FOR Supply and delivery of Dust Handling Plant Auxiliary spares (DHP) at Matimba Power Station for a period of 60 months on an as and when required basis.	Template Identifier	32-726- 03T	Rev	1
		Document Identifier	E2987GX LPMAT	Rev	1
		Effective Date	April 2022		

Contract Name: Supply and delivery of Dust Handling Plant Auxiliary spares (DHP) at Matimba Power Station for a period of 60 months on an as and when required basis

Contract Address: Matimba Power Station, Nelson Mandela drive Lephalale 0555

Name: Mosale Madisha
Eskom Safety Officer
Signature: 
Date: 2026-06-12

Name: Sipho Honono
Eskom Contractor Manager
Signature: 
Date 2026/06/15

Name: Simon Mavhungu
Eskom Safety Manager
Signature: 
Date 2026.06.23

Public

When downloaded from the document management system, this document is uncontrolled and the responsibility rests with the user to ensure it is in line with the authorised version on the system.

No part of this document may be reproduced without the expressed consent of the copyright holder, Eskom Holdings SOC Ltd, Reg No 2002/015527/30.

	GENERATION COAL FIRED STATIONS OHS SPECIFICATION FOR Supply and delivery of Dust Handling Plant Auxiliary spares (DHP) at Matimba Power Station for a period of 60 months on an as and when required basis.	Template Identifier	32-726- 03T	Rev	1
		Document Identifier	E2987GX LPMAT	Rev	1
		Effective Date	April 2022		

Table of Contents

1. INTRODUCTION	5
2. SUPPORTING CLAUSES	5
2.1 SCOPE	5
2.1.1 Purpose	5
2.1.2 Applicability	5
2.2 NORMATIVE/INFORMATIVE REFERENCES	6
2.2.1 Normative	6
2.2.2 Informative	7
2.3 DEFINITIONS	7
2.4 ABBREVIATIONS	11
2.5 RELATED/SUPPORTING DOCUMENTS	11
3. DOCUMENT CONTENT	12
3.1 SCOPE OF WORK	12
3.2 LEGAL COMPLIANCE	12
3.2.1 Section 37(2) (Legal) Agreement	12
3.2.2 Hazardous Work by Children (Child Labour)	12
3.2.3 OHS Act	13
3.2.4 Legislative Compliance	13
3.3 ESKOM REQUIREMENTS	13
3.4 SHEQ POLICY	13
3.5 COVID -19 POLICY	13
3.5.1 Covid -19 requirements	14
3.6 COID	14
3.7 COSTING FOR OHS WITHIN THE CONTRACT	14
3.8 STATUTORY APPOINTMENTS	14
3.8.1 Non statutory appointments	Error! Bookmark not defined.
3.9 ESKOM LIFE-SAVING RULES	15
3.10 SUBSTANCE ABUSE	17
3.11 CONTRACTOR ORGANISATIONAL STRUCTURE	18
3.11.1 Main Contractor Organogram	18
3.11.2 Appointed Contractor/s Organogram	18
3.12 ROLES AND RESPONSIBILITIES	18
Commitment	18
3.12.1 Main contractors and appointed contractors	19
3.12.2 Contractor site supervisor	20
The contractor site supervisor must be trained in the following:	20
HIRA, Incident investigation training, Supervisor training, authorised person & PSR, Legal liability	20

Public

When downloaded from the document management system, this document is uncontrolled and the responsibility rests with the user to ensure it is in line with the authorised version on the system.

No part of this document may be reproduced without the expressed consent of the copyright holder, Eskom Holdings SOC Ltd, Reg No 2002/015527/30.

	GENERATION COAL FIRED STATIONS OHS SPECIFICATION FOR Supply and delivery of Dust Handling Plant Auxiliary spares (DHP) at Matimba Power Station for a period of 60 months on an as and when required basis.	Template Identifier	32-726- 03T	Rev	1
		Document Identifier	E2987GX LPMAT	Rev	1
		Effective Date	April 2022		

3.12.3 Contractor Health and Safety officer Parttime or as when required	21
3.13 RISK ASSESSMENT (REFER TO 32-520)	22
3.14 SAFE WORK PROCEDURES / METHOD STATEMENTS	23
3.15 ROOF WORK (REFER TO 32- 418) (IF APPLICABLE)	24
3.16 FIRE EQUIPMENT AND MAINTENANCE	24
3.17 FLAMMABLE AND COMBUSTIBLE LIQUIDS	24
3.17.1 Refuelling at Eskom sites	25
3.18 FIRST AID AND EQUIPMENT	25
3.18.1 Boxes and equipment	26
3.19 OHS COMMUNICATION SYSTEMS	26
3.19.1 Statutory Health and Safety Committees	26
3.19.2 Non-statutory health and safety committees	27
3.20 TOOL BOX TALKS / DAILY TEAM TALKS / PRE JOB MEETINGS	29
3.21 OHS TRAINING	29
3.21.1 Main Contractor Induction training	29
The contractor is required to induct its employees and make arrangements with the Business Unit for its employees to attend induction in order to be granted permission to access site. Company and Client induction shall be renewed annually	29
3.21.2 Appointed Contractor induction training	30
3.21.3 Visitors to site induction	30
3.22 GENERAL TRAINING	30
3.23 CONTRACTOR SITE ESTABLISHMENT	30
3.23.1 WHERE CONTRACTORS ARE PROVIDING THEIR OWN FACILITIES, THE FOLLOWING SHALL APPLY:	30
3.23.2 WHERE ESKOM IS MAKING PROVISION OF THE FACILITIES TO THE CONTRACTOR, THE FOLLOWING SHALL APPLY:	31
3.24 SITE ROADS	31
3.25 VEHICLE MANAGEMENT	31
3.26 HOUSEKEEPING AND ORDER	32
3.27 STACKING AND STORAGE	33
3.28 WORKPLACE SIGNAGE AND COLOUR CODING	33
3.29 TOOLS AND EQUIPMENT	34
3.29.1 Hand tools	34
3.30 LADDERS	35
3.31 SCAFFOLDING (IF APPLICABLE)	35
3.32 AUDITING	36
3.32.1 Approval and compliance of Main contractor OHS plan	36
3.32.2 Eskom OHS audits	36
3.32.3 Contractor audits	36
3.33 SMOKING	37
3.34 CELLULAR PHONES	37
3.35 OCCUPATIONAL HEALTH, HYGIENE AND REHABILITATION	37
3.35.1 Medical Assessments	37
3.36 ROLES AND RESPONSIBILITIES	38
3.37 WORKING AT HEIGHTS	38
3.37.1 General Requirements	38
A drop zone shall be established with appropriate warning signs and barricading, warning personnel below of workers above and potential falling objects.	38
Every employer shall ensure that work at height is:	38
3.38 CONFINED SPACES	39

Public

When downloaded from the document management system, this document is uncontrolled and the responsibility rests with the user to ensure it is in line with the authorised version on the system.

No part of this document may be reproduced without the expressed consent of the copyright holder, Eskom Holdings SOC Ltd, Reg No 2002/015527/30.

	GENERATION COAL FIRED STATIONS OHS SPECIFICATION FOR Supply and delivery of Dust Handling Plant Auxiliary spares (DHP) at Matimba Power Station for a period of 60 months on an as and when required basis.	Template Identifier	32-726- 03T	Rev	1
		Document Identifier	E2987GX LPMAT	Rev	1
		Effective Date	April 2022		

1. THE CONTRACTOR SHALL ENSURE THAT THEY COMPLY WITH THE PLANT SAFETY REGULATION (240-150642762) IN RELATION TO THE CONFINED SPACES.	39
2. THE CONTRACTOR MUST ENSURE THAT AT LEAST ONE PERSON OR THERE IS A RESPONSIBLE PERSON WHO IS TRAINED ON WORK THAT WILL BE CARRIED IN THE CONFINED SPACES, ALSO TO RESCUE AND CONDUCT THE RISK ASSESSMENT. 39	
3. THE CONTRACTOR MUST ENSURE THAT THE STATION RESCUE EMERGENCY NUMBER IS ALWAYS AVAILABLE.	39
3.39 PERSONAL PROTECTIVE EQUIPMENT REQUIREMENTS.....	39
3.40 INCIDENT INVESTIGATION	40
3.40.1 STATISTICAL REPORTING.....	40
3.40.2 PLANNED TASK OBSERVATIONS	41
3.41 EMERGENCY MANAGEMENT	41
3.42 NON-CONFORMANCE AND COMPLIANCE.....	41
3.43 OHS FILES	42
3.44 WORK STOPPAGE	42
3.45 HOURS OF WORK.....	42
3.45.1 Normal work.....	43
3.45.2 Night work	43
3.45.3 Overtime	43
3.46 OMISSIONS FROM SAFETY AND HEALTH REQUIREMENTS SPECIFICATION	43
3.47 CONTRACTOR PERFORMANCE MONITORING	43
3.48 CONTRACT SIGN OFF	44
3.49 ESKOM'S RIGHT TO TERMINATE THE CONTRACT	44
5. REVISIONS.....	44
6. DEVELOPMENT TEAM.....	44

Public

When downloaded from the document management system, this document is uncontrolled and the responsibility rests with the user to ensure it is in line with the authorised version on the system.

No part of this document may be reproduced without the expressed consent of the copyright holder, Eskom Holdings SOC Ltd, Reg No 2002/015527/30.

	GENERATION COAL FIRED STATIONS OHS SPECIFICATION FOR Supply and delivery of Dust Handling Plant Auxiliary spares (DHP) at Matimba Power Station for a period of 60 months on an as and when required basis.	Template Identifier	32-726- 03T	Rev	1
		Document Identifier	E2987GX LPMAT	Rev	1
		Effective Date	April 2022		

1. INTRODUCTION

Eskom's responsibility and commitment is to ensure a safe working environment is in line with its Safety, Health, Environmental, and Quality (SHEQ) Policy and applicable legislative obligations. This OHS specification is Eskom Generation's minimum requirements which are required to be met for the duration of the contract period by contractors/suppliers and, where required, the delivery organisation. The contractor is expected to develop an OHS plan that meets these requirements as well as all the relevant applicable legislation that they conform to. Eskom in no way assumes the contractor's legal responsibilities and liabilities. The contractor is and remains accountable for the quality and execution of their health and safety programme for their employees and appointed contractor employees. This OHS specification reflects minimum requirements and should not be construed as all-encompassing.

Note 1: All the requirements listed hereunder are in relation to the contract and do not supersede or replace any organizational OHS requirements.

Where requirements listed are already in place, then the organizational requirements must be taken cognisance of and listed in the respective OHS plans. If there are any additional Eskom and/or legislative requirements listed in the OHS specification, then these must be addressed.

2. SUPPORTING CLAUSES

2.1 SCOPE

This OHS specification lists the legislative and Eskom requirements and, where applicable, any requirements pertaining to local authorities, municipal by-laws, or environmental legislation that must be met by the contractor.

2.1.1 Purpose

This document will provide a standardised approach to the compilation of OHS specifications throughout Eskom Generation business for contracts, standards, and NEC 3.

2.1.2 Applicability

This OHS specification is applicable to any contracting organisation that intends to respond to Eskom Generation's tender/enquiry with the intention of entering into a contract.

Public

When downloaded from the document management system, this document is uncontrolled and the responsibility rests with the user to ensure it is in line with the authorised version on the system.

No part of this document may be reproduced without the expressed consent of the copyright holder, Eskom Holdings SOC Ltd, Reg No 2002/015527/30.

	GENERATION COAL FIRED STATIONS OHS SPECIFICATION FOR Supply and delivery of Dust Handling Plant Auxiliary spares (DHP) at Matimba Power Station for a period of 60 months on an as and when required basis.	Template Identifier	32-726- 03T	Rev	1
		Document Identifier	E2987GX LPMAT	Rev	1
		Effective Date	April 2022		

2.2 NORMATIVE/INFORMATIVE REFERENCES

Parties using this document shall apply the most recent edition of the documents listed in the following paragraphs.

2.2.1 Normative

- [1] 240-167170392: The Framework for Developing a Safety, Health and Environmental (SHE) Specification/Requirements Specific to Project Type and Site
 - [2] 32-727: Safety, Health, Environment and Quality Policy
 - [3] 240-62196227: Life-saving Rules Standard
 - [4] Occupational Health and Safety Act and Regulations No 85 of 1993 and its Regulations
 - [5] Construction Regulations of 2014 or latest edition as per government gazette.
 - [6] Mine Health & Safety Act No. 29 of 1996 and Regulations
 - [7] OHS Act 85 of 1993 and its regulations.
 - [8] The Constitution of the Republic of South Africa (particularly Section 24 of the Bill of Rights)
 - [9] Civil and Building Work Act
 - [10] Compensation for Occupational Injuries and Diseases Act
 - [11] National Road Traffic Act, 1996 (Act No. 93 of 1996)
 - [12] 32-95 Eskom Occupational Health and Safety Incident Management procedure
 - [13] The Vehicle and Driver Safety Management Procedure (240-62946386)
 - [14] 32-345 Eskom Vehicle Safety Specification.
 - [15] 32-37 Substance Abuse Procedure
 - [16] All relevant South African legislation (national, provincial, and local)
 - [17] Applicable South African National Standards (SANS) for the scope of work/Project.
 - [18] Applicable International Standards
 - [19] Licenses/Permits
 - [20] 32-345 Eskom Vehicle Safety Specification
 - [21] 240-54937439: Fire Protection/Detection Assessment Standard.
 - [22] 32-124 Eskom Fire Risk Management
 - [23] 240-43848327 Employees' right of refusal to work in an unsafe situation.
 - [24] 32-418: Working from Heights Procedure
 - [25] 240-100979499: Personal Protective Equipment for work at Heights Specification
 - [26] 32-123: Emergency Planning
 - [27] 32-407 Behaviour Safety Observation Procedure
 - [28] 32-726: Contract and Contractor OHS Management
 - [29] 39-98: Safe use of Lifting Machines
 - [30] 32-1126 Eskom Smoking Policy
 - [31] 32-1134 Access Control at Eskom Premises
 - [32] 240-44175132 Eskom Personal Protective Equipment Specification (PPE)
 - [33] 32-477 Safety, Health and Environment Training and Development Procedure
 - [34] 240-43921084- Fall arrester checklist
 - [35] Eskom Operating Regulations for High Voltage Systems
 - [36] Eskom Plant Safety Regulations (Low Voltage Regulations)
- The list of legislation and documents for further information is not exhaustive and/or not limited to the legislation and documents listed above.

Public

When downloaded from the document management system, this document is uncontrolled and the responsibility rests with the user to ensure it is in line with the authorised version on the system.

No part of this document may be reproduced without the expressed consent of the copyright holder, Eskom Holdings SOC Ltd, Reg No 2002/015527/30.

	GENERATION COAL FIRED STATIONS OHS SPECIFICATION FOR Supply and delivery of Dust Handling Plant Auxiliary spares (DHP) at Matimba Power Station for a period of 60 months on an as and when required basis.	Template Identifier	32-726- 03T	Rev	1
		Document Identifier	E2987GX LPMAT	Rev	1
		Effective Date	April 2022		

2.2.2 Informative

Note: The following is a list of documents that can be used as a guide in order to meet legal and

Eskom requirements

[1] ISO 45001:2018, Occupational Health and Safety Management Systems-Requirements (Contractor shall use as guideline)

[2] Relevant South African National Standards for the task/Project.

[3] Relevant Occupational Health and Safety legislations required in accordance with the scope of the project.

2.3 DEFINITIONS

Public

When downloaded from the document management system, this document is uncontrolled and the responsibility rests with the user to ensure it is in line with the authorised version on the system.

No part of this document may be reproduced without the expressed consent of the copyright holder, Eskom Holdings SOC Ltd, Reg No 2002/015527/30.

	GENERATION COAL FIRED STATIONS OHS SPECIFICATION FOR Supply and delivery of Dust Handling Plant Auxiliary spares (DHP) at Matimba Power Station for a period of 60 months on an as and when required basis.	Template Identifier	32-726-03T	Rev	1
		Document Identifier	E2987GX LPMAT	Rev	1
		Effective Date	April 2022		

Definition	Explanation
Appointed contractor	Means a contractor appointed by the Main contractor
Baseline risk assessment	(32-520) baseline operational risks refer to the health and safety risks associated with all standard processes and routine activities in the business
Business unit (BU)	(32-296) means any defined unit within the Eskom environment, operating as a business under a particular cost-centre number. In the context of this document and in terms of health and safety, any reference to a BU includes a defined unit within any Eskom division and its subsidiaries
Client	(OHS Act) Eskom representative (Internal – Asset Owner), also referred to as the contract administrator/custodian or agent or contract manager (as defined in the contract). He/she is the person responsible for ensuring that the works or services are executed in terms of the contract, as well as adherence to legislation pertaining to the contract.
Competent person	(OHS Act) means any person having the knowledge, training, experience, and qualifications, specific to the work or task being performed, provided that, where appropriate, qualifications and training are registered in terms of the South African Qualifications Authority Act, 1995 (Act No. 58 of 1995)
Contractor	(OHS Act) means an employer as defined in section 1 of the Act who performs contracted work and includes Main contractors
Contract's Manager/End User	Contract's Manager/End User
Consultant	means a person providing professional advice
Controlled disclosure	controlled disclosure to external parties (either enforced by law or discretionary)
Duty of care to the environment	(32-136) anybody who causes or has caused or may cause significant pollution or degradation of the environment must take reasonable measures to prevent such pollution or degradation from occurring, continuing, or recurring. If such harm to the environment is authorised by law or cannot reasonably be avoided or stopped, such person must minimise and rectify such pollution or degradation of the environment
Employee	(OHS Act) means, subject to the provisions of subsection (2), any person who is employed by or works for an employer and who receives or is entitled to receive any remuneration or who works under the direction or supervision of an employer or any other person
Employer	(OHS Act) means, subject to the provisions of subsection (2), any person who employs or provides work for any person and remunerates that person or expressly or tacitly undertakes to remunerate him/her, but excludes a TES (ex labour broker) as defined in section 1(1) of the Labour Relations Act 1956 (Act No. 28 of 1956)

Public

When downloaded from the document management system, this document is uncontrolled and the responsibility rests with the user to ensure it is in line with the authorised version on the system.

No part of this document may be reproduced without the expressed consent of the copyright holder, Eskom Holdings SOC Ltd, Reg No 2002/015527/30.

	GENERATION COAL FIRED STATIONS OHS SPECIFICATION FOR Supply and delivery of Dust Handling Plant Auxiliary spares (DHP) at Matimba Power Station for a period of 60 months on an as and when required basis.	Template Identifier	32-726-03T	Rev	1
		Document Identifier	E2987GX LPMAT	Rev	1
		Effective Date	April 2022		

Definition	Explanation
Environment	(32-94) means: a) the land, water, and atmosphere of the earth; b) micro-organisms and plant and animal life; and c) any part or combination of (a) and (b) and the interrelationships among and between them, and the physical, chemical, aesthetic, and cultural properties and conditions of the foregoing that influence human health and well-being
Eskom requirements	Eskom requirements flowing from directives, policies, standards, procedures, specifications, work instructions, guidelines, or manuals
Fall protection plan	(OHS Act) means a documented plan of all risks relating to working from an elevated position, considering the nature of work undertaken, and setting out the procedures and methods to be applied in order to eliminate the risk
Hazard	(OHS Act) means a source of, or exposure to, danger
Hazard identification	(OHS Act) means the identification and documenting of existing or expected hazards to the health and safety of persons, which are normally associated with the type of construction work being executed or to be executed
Occupational Health and safety file	(OHS Act) means a file or other record in permanent form, containing the information required in relation to the contract.
Health and safety plan	(OHS Act) means a document plan that addresses hazards identified and includes safe work procedures to mitigate, reduce, or control hazards identified
Occupational Health and safety specification	(OHS Act) means a document specification of all health and safety requirements pertaining to associated to a contract, so as to ensure the health and safety of persons.
Occupational Health and safety requirements	means comprehensive health and safety requirements for a contract, contract, site, and scope of work. This specification is intended to ensure the health and safety of persons, both workers and the public, and the duty of care to the environment. The health and safety requirements must be specific to each contract, contract, site, and scope of work
Lifesaving Rules	(240-62196227) a rule that, if not adhered to, has the potential to cause serious harm to people
Medical Certificate of fitness	(OHS Act) means a certificate valid for one year, issued by an occupational health practitioner, issued in terms of the regulations, whom shall be registered with the Health Professions Council of South Africa
Medical surveillance	(OHS Act) means a planned programme or periodic examination (which may include clinical examinations, biological monitoring, or medical tests) of employees by an occupational health practitioner or, in prescribed cases, by an occupational medicine practitioner
Method statement	(OHS Act) means a written document detailing the key activities to be performed in order to reduce, as reasonably as practicable, the hazards identified in any risk assessment

Public

When downloaded from the document management system, this document is uncontrolled and the responsibility rests with the user to ensure it is in line with the authorised version on the system.

No part of this document may be reproduced without the expressed consent of the copyright holder, Eskom Holdings SOC Ltd, Reg No 2002/015527/30.

	GENERATION COAL FIRED STATIONS OHS SPECIFICATION FOR Supply and delivery of Dust Handling Plant Auxiliary spares (DHP) at Matimba Power Station for a period of 60 months on an as and when required basis.	Template Identifier	32-726-03T	Rev	1
		Document Identifier	E2987GX LPMAT	Rev	1
		Effective Date	April 2022		

Definition	Explanation
National Enquiries/contracts	sourcing of services providers/contractors at the divisional level and not at BU level thorough tendering, request for price etc
Organisation	may be defined as a group of individuals (large of small) that is cooperating under the direction of executive leadership in accomplishment of certain common objects
Pre-job meetings	(34-227) means a meeting that is held prior to the commencement of the day's work and that is attended by all the relevant employees associated with the work task
Main contractor	(In the text of this document) Means an employer, as defined in section 1 of the OHS Act, who intends to tender for or has signed a contract with Eskom for services rendered.
Provincial director	(OHS Act) means the provincial director as defined in Regulation 1 of the General Administrative Regulations under the Act
Responsible Manager	Is a Manager of a department, section or operating/business unit who has been appointed as part of the Eskom delegation of authority process with the aim to assist the applicable 16(2) assigned person in executing his/her duties in terms of the Occupational Health and Safety Act
Risk assessment	(OHS Act) means a programme to determine any risk associated with any hazard at a construction site in order to identify the steps needed to be taken to remove, reduce, or control such hazard.
Site	(34-228) means an Eskom department, unit, complex, building, specific contract, work site, or the site where agents, clients, Main contractors, contractors, suppliers, vendors, and service providers provide a service to Eskom, directly or indirectly
Service provider	any private person or legal entity that provides any service(s) to Eskom for compensation
Subsidiary	(32-94) an enterprise controlled by another (called the parent) through the ownership of greater than 50% of its voting stock
Supplier	(32-1034) means a natural or legal person who renders a service and may include the following current or potential supplier vendor, contractor, consultant
Task	(34-227) a segment of work that requires a set of specific and distinct actions for its completion
Toolbox talks	(34-227) where the team leader, after conducting pre-task planning, shares all the tasks at hand and discusses task allocation, the identified risks, and the control measures with all his/her team members on site before commencing a specific task and documenting the agreed strategy. (This shall be done to ensure common understanding of the tasks, risks, and control measures required.)
The Act	(OHS Act) means the Occupational Health and Safety Act No. 85 of 1993, as amended, and the Regulations thereto

Public

When downloaded from the document management system, this document is uncontrolled and the responsibility rests with the user to ensure it is in line with the authorised version on the system.

No part of this document may be reproduced without the expressed consent of the copyright holder, Eskom Holdings SOC Ltd, Reg No 2002/015527/30.

	GENERATION COAL FIRED STATIONS OHS SPECIFICATION FOR Supply and delivery of Dust Handling Plant Auxiliary spares (DHP) at Matimba Power Station for a period of 60 months on an as and when required basis.	Template Identifier	32-726- 03T	Rev	1
		Document Identifier	E2987GX LPMAT	Rev	1
		Effective Date	April 2022		

Definition	Explanation
Visitor	any person visiting a workplace with the knowledge of, or under the supervision of, an employer.

2.4 ABBREVIATIONS

Abbreviation	Description
BU	Business Unit
CE	Chief Executive
COID Act	Compensation for Occupational Injuries and Diseases Act
DMR	Driven Machinery Regulations
DEL	Department of Employment and Labour (Inspection and Enforcement services – Provincial office)
EP	Emergency Preparedness
EAP	Employee Assistance Program
ERfW	Environmental Regulations for Workplaces
GAR	General Administrative Regulations
GSR	General Safety Regulations
HCS	Hazardous Chemical Substances
LDV	Light Delivery Vehicle
MSDS	Material Safety Data Sheets
OHS Act	Occupational Health and Safety Act and Regulations, 85 of 1993
O&M	Operating and Maintenance
LoG	(COID) Letter of Good Standing
SABS	South African Bureau Standard
SANS	South African National Standard

2.5 RELATED/SUPPORTING DOCUMENTS

Section 37(2) of the OHS Act requires Eskom to sign an agreement and include it in the OHS file for evaluation prior to the start of work. OHS department will issue the 37(2) agreement to the contract manager/end user who will facilitate the signing of the document by Eskom and contractor representatives.

Public

When downloaded from the document management system, this document is uncontrolled and the responsibility rests with the user to ensure it is in line with the authorised version on the system.

No part of this document may be reproduced without the expressed consent of the copyright holder, Eskom Holdings SOC Ltd, Reg No 2002/015527/30.

	GENERATION COAL FIRED STATIONS OHS SPECIFICATION FOR Supply and delivery of Dust Handling Plant Auxiliary spares (DHP) at Matimba Power Station for a period of 60 months on an as and when required basis.	Template Identifier	32-726- 03T	Rev	1
		Document Identifier	E2987GX LPMAT	Rev	1
		Effective Date	April 2022		

3. DOCUMENT CONTENT

3.1 SCOPE OF WORK

Supply and delivery of Dust Handling Plant Auxiliary spares (DHP) at Matimba Power Station for a period of 60 months on an as and when required basis

A copy of the scope of work must be retained by the contractor.

Note: The contractor who will be awarded this contract will be known as the “Main contractor” and any contractor appointed by the Main contractor will be known as the “Appointed contractor”

3.2 LEGAL COMPLIANCE

3.2.1 Section 37(2) (Legal) Agreement

A section 37(2) agreement must be signed between Eskom and the main contractor at the time of submitting the safety file. The main contractor must ensure that a section 37(2) agreement is compiled between the main contractor and all their appointed contractors for the contract. The original copy of the section 37(2) agreement must be retained by the contractor, and a copy must be retained by the responsible contract manager/end user. A copy of all the agreements must form part of the respective contractor's OHS file.

3.2.2 Hazardous Work by Children (Child Labour)

The constitution of the Republic of South Africa, in the "Bill of Rights", is clear on the rights of children, especially when it comes to:

1. *being protected from exploitative labour practices.*
2. *not be required or permitted to perform work or provide services that*
3. *are inappropriate for a person of that child's age; or*
4. *This places at risk the child's well-being, education, physical or mental health, or spiritual, moral, or social development* and the Basic Conditions of Employment Act, Chapter six, Section 43, "Prohibition of employment of children."

Before resorting to the use of child labour, due consideration must be given to the child's constitutional rights. Where work is being performed which is not prohibited in terms of the constitution, then such work must be conducted in terms of the OHS Act "Regulations on Hazardous Work by Children in South Africa" with emphasis on paragraph 2: Purpose and Interpretation. Eskom does not condone the use of child labour and, therefore, all effort must be exercised, and child labour should not be used.

Public

When downloaded from the document management system, this document is uncontrolled and the responsibility rests with the user to ensure it is in line with the authorised version on the system.

No part of this document may be reproduced without the expressed consent of the copyright holder, Eskom Holdings SOC Ltd, Reg No 2002/015527/30.

	GENERATION COAL FIRED STATIONS OHS SPECIFICATION FOR Supply and delivery of Dust Handling Plant Auxiliary spares (DHP) at Matimba Power Station for a period of 60 months on an as and when required basis.	Template Identifier	32-726-03T	Rev	1
		Document Identifier	E2987GX LPMAT	Rev	1
		Effective Date	April 2022		

3.2.3 OHS Act

The main contractor and appointed contractors shall have an up-to-date copy of the OHS Act and regulations which will be available to all employees.

3.2.4 Legislative Compliance

All contractors will comply with all the legislation pertaining to this contract being:

The Main contractor and all appointed contractors will comply with all the legislation pertaining to this contract being:

- The Constitution of the Republic of South Africa (particularly Section 24 of the Bill of Rights).
- Occupational Health and Safety Act 1993 (Act 85 of 1993) and its Regulations.
- National Environmental Management Act 1998 (Act 107 of 1998).
- Environment Conservation Act 1989 (Act 73 of 1989).
- National Water Act 1998 (Act 36 of 1998).
- Civil and Building Work Act.
- National Road Traffic Act 93 of 1996.
- Compensation for Occupational Injuries and Diseases Act.
- SANS Standards –Contractor shall use the relative standards applicable to the contract.

3.3 ESKOM REQUIREMENTS

All contractors shall, before commencement of the contract ensure that all their employees are familiar with the relevant Eskom OHS documentation that is applicable to contract services.

3.4 SHEQ POLICY

A SHEQ policy is a statement of intent and a commitment by the organization's CE and senior management in relation to the relevant OHS roles and responsibilities, the achievement of their strategic objectives, and values of integrity, customer satisfaction, excellence, and innovation. The main contractor and all appointed contractors, if not already in place, will be required to compile an organisational SHEQ policy in line with their OHS responsibilities. The policy must be signed by the organisation's CE or the appointed assistant to the CE, OHS Act Section 16(2). The policy must be displayed in a prominent place within the workplace. A copy of the policy must be filed in the contractor's OHS files and attached as an annexure to the OHS Plan.

3.5 COVID -19 POLICY

Due to the current pandemic the contractors are required to submit the Covid policy signed by the most senior person. The policy must be displayed in a prominent place within the workplace. A copy of the policy must be filed in the contractor's OHS files and attached as an annexure to the OHS Plan.

Public

When downloaded from the document management system, this document is uncontrolled and the responsibility rests with the user to ensure it is in line with the authorised version on the system.

No part of this document may be reproduced without the expressed consent of the copyright holder, Eskom Holdings SOC Ltd, Reg No 2002/015527/30.

	GENERATION COAL FIRED STATIONS OHS SPECIFICATION FOR Supply and delivery of Dust Handling Plant Auxiliary spares (DHP) at Matimba Power Station for a period of 60 months on an as and when required basis.	Template Identifier	32-726-03T	Rev	1
		Document Identifier	E2987GX LPMAT	Rev	1
		Effective Date	April 2022		

3.5.1 Covid -19 requirements

Covid-19 costs are not for profit making purpose and Eskom reserves the right to accept and/or decline the list of PPE which will be listed in the detailed Covid-19 costs. Due to the current pandemic the contractors are required to provide Eskom with a Covid-19 risk assessment and a detailed plan on how to prevent the spread of the virus and what control measures will be put in place to protect Eskom employees and members of the public. The risk assessment must include the following but not limited to, adherence to Covid-19 protocols in designated smoking areas. Covid-19 costs are applicable for the duration of the pandemic and the Covid-19 costs will be ceased once the country has declared that Covid-19 is no more a pandemic. The contractors have an obligation to comply with the National Disaster Management Act including the appointment of the Compliance Officer.

3.6 COID

The Main contractor and all his/her appointed contractors shall be registered with an appropriate employment compensation commissioner and have available a valid letter of good standing (LoG) from such commissioner. The obligation lies with the contractors to ensure that the LoG remain valid throughout the contract period. A copy of the LoG must be filed in the contractor OHS files.

3.7 COSTING FOR OHS WITHIN THE CONTRACT

The costing for OHS must be itemised based on the overall scope of the contract (i.e.) Training, provision of PPE, safety equipment purchases etc.

3.8 STATUTORY APPOINTMENTS

The Main contractor and all appointed contractors must appoint competent workers who will comply with the OHS Act for the duration of the contract. Before requiring appointees to accept an appointment, the employer must ensure that they have received appropriate training and/or information about their responsibilities. The relevant statutory appointments must be made in compliance with the OHS Act's criteria, which include appointing a qualified individual to the appropriate roles. The following should be included in the statutory appointments, but not limited to:

- OHS Act General Administrative Regulation 9(2) – Incident Investigator

Public

When downloaded from the document management system, this document is uncontrolled and the responsibility rests with the user to ensure it is in line with the authorised version on the system.

No part of this document may be reproduced without the expressed consent of the copyright holder, Eskom Holdings SOC Ltd, Reg No 2002/015527/30.

	GENERATION COAL FIRED STATIONS OHS SPECIFICATION FOR Supply and delivery of Dust Handling Plant Auxiliary spares (DHP) at Matimba Power Station for a period of 60 months on an as and when required basis.	Template Identifier	32-726-03T	Rev	1
		Document Identifier	E2987GX LPMAT	Rev	1
		Effective Date	April 2022		

3.9 ESKOM LIFE-SAVING RULES

1. Eskom places a high value on health and safety and urges every organization that undertakes work for Eskom to do the same.
2. Eskom has developed five life-saving guidelines that will apply to all Eskom employees, agents, consultants, and contractors. Any Eskom employee or employee of a Main Contractor or appointed contractor who fails to follow these rules would be deemed a serious violation. These rules are in place to protect any employee, labour broker, or contractor working from significant injury or death.
3. If any contractual work (including delivery of any product) is to be undertaken on Eskom premises, the rules shall be obeyed by any contractor and their employees.

The rules are:

RULE	DESCRIPTION OF RULE
Rule 1	RULE 1: OPEN, ISOLATE, TEST, EARTH AND CREATE AN EQUIPOTENTIAL ZONE BEFORE TOUCH To ensure a safe electrical work environment, no person may work/operate on, around or near any electrical network, line or apparatus, electrically connected to the power system and/or electrically charged and/or not electrically charged unless: a) He/she is trained and authorised as competent for the task to be done. b) There is a valid permit to work where required and they are being supervised by a competent person. c) A pre-task risk assessment to identify all risks and hazards has been conducted before any work commences. d) He/she follows the requirements on OPEN, ISOLATE, TEST, EARTH, AND CREATE AN EQUIPOTENTIAL ZONE BEFORE TOUCH, based on applicable/related standards, procedures and outcome of risk assessment fit for the type of work or task to be performed. e) The work area shall be within the equipotential zone, with the working earth visible at all times. f) The authorised person has physically shown all team members that the apparatus is safe to work on. g) He/she makes the specific electrical environment safe before performing the work; and h) All the appropriate PPE (including face shield and insulated gloves for low voltage work) are worn. Note: The equipotential zone is only applicable for work being done on medium and high voltage apparatus.

Public

When downloaded from the document management system, this document is uncontrolled and the responsibility rests with the user to ensure it is in line with the authorised version on the system.

No part of this document may be reproduced without the expressed consent of the copyright holder, Eskom Holdings SOC Ltd, Reg No 2002/015527/30.

	GENERATION COAL FIRED STATIONS OHS SPECIFICATION FOR Supply and delivery of Dust Handling Plant Auxiliary spares (DHP) at Matimba Power Station for a period of 60 months on an as and when required basis.	Template Identifier	32-726-03T	Rev	1
		Document Identifier	E2987GX LPMAT	Rev	1
		Effective Date	April 2022		

Rule 2	RULE 2: HOOK UP AT HEIGHT Working at height is a significant part of work in Eskom Holdings and is regarded as a high-risk activity, as a result, all precautions must be taken to prevent incidents while working at height. Wherever reasonably practicable, preference must be given to the performance of work at ground level as opposed to work in an elevated position. Where work in an elevated position is necessary, the requirements in this document and all other Eskom requirements pertaining to working from height shall apply. No person may work at height where there is a risk of falling unless: a) A Fall Protection Plan has been developed by a trained fall protection plan developer and communicated to all employees working at height based on the scope of work/task. b) He/she is medically fit to work at height. c) He/she is trained in accordance with Eskom's requirements for working at height d) A pre-task-specific work at height risk assessment to identify all risks and hazards has been conducted and communicated to all participants before commencing any work of this nature. e) He/she appropriately conducts work as determined by the risk assessment. f) He/she is appropriately secured during ascending and descending where applicable; and g) He/she is using an Eskom-approved fall arrest system where applicable.
Rule 3	RULE 3: BUCKLE UP Where required, the proper wearing of seat belts for any driver, operator and passenger is mandatory in all vehicles/equipment when driving and/or travelling for Eskom business purposes. The driver is obligated to ensure that he/she as well as all passengers are properly seated and wearing their seatbelts at all times while being transported in the vehicle, as per Eskom specifications. Note: This rule is applicable on any road or parking lot, irrespective of the speed, and when the vehicle moves in a forward or backward direction.
Rule 4	RULE 4: BE SOBER No person who is under the influence or who appears to be under the influence of intoxicating liquor or drugs will be permitted to enter or remain on an Eskom site conduct Eskom business or drive/operate a vehicle/equipment for Eskom business purposes. This includes any level of alcohol or the presence of any drugs, controlled substances, and/or illegal substances in the body that impairs or could impair mental and physical functioning, irrespective of when the substance was used.
Rule 5	RULE 5: ENSURE THAT YOU HAVE A PERMIT TO WORK No person shall work without the required Permit to Work (PTW), which is governed by but not limited to: a) Plant Safety Regulations; or b) Operating Regulations for High Voltage Systems (ORHVS) (handover or permit); or

Public

When downloaded from the document management system, this document is uncontrolled and the responsibility rests with the user to ensure it is in line with the authorised version on the system.

No part of this document may be reproduced without the expressed consent of the copyright holder, Eskom Holdings SOC Ltd, Reg No 2002/015527/30.

	GENERATION COAL FIRED STATIONS OHS SPECIFICATION FOR Supply and delivery of Dust Handling Plant Auxiliary spares (DHP) at Matimba Power Station for a period of 60 months on an as and when required basis.	Template Identifier	32-726-03T	Rev	1
		Document Identifier	E2987GX LPMAT	Rev	1
		Effective Date	April 2022		

	c)Low Voltage Operating Regulations; or d)Any other activity where a permit is required, for example, driver and statutory permits. No apparatus is to be returned to service without the cancellation of all permits on that plant in accordance with procedure, unless permission is granted for a particular plant to be returned to service with permits still open, like in the case of redundant systems. NOTE: In the case of live work, a “Live Work Declaration Form” is to be completed by the authorised person, who is the person responsible for the safe execution of work according to relevant standards and procedures.
Rule 6	RULE 6: ENSURE SAFE LIVE WORKING To ensure safe live work, each live worker shall: a) Ensure all live work basic principles are adhered to, as outlined (for the method being used) in the High Voltage Live Working Standard for the respective division. b) Observe and maintain the minimum approach distance (MAD). c)Only perform live work (never mix live and dead work on the same site at the same time – Refer to ORHVS Section 7 and 5 handouts respectively). d)Perform tasks they are authorised for and only undertake tasks that are documented in the respective Task Manual (TM). Only work on one potential (voltage) at a time.

Consequences of Violating a Life-Saving Rule

In terms of general health and safety in Eskom, if any of the Life-Saving Rules are violated, it will be treated as serious misconduct, and result in a disciplinary process in accordance with the Eskom Disciplinary Code and Procedure.

It must be highlighted that Eskom takes a ZERO TOLERANCE stance to violation of these rules.

Depending on the circumstances, Eskom reserves the right, where a contractor manager/supervisor allows the violation of a Life-Saving Rule, to suspend the contractor's activities while determining an appropriate sanction.

Where a contractor employee allegedly violates a Life-Saving Rule, the contractor shall immediately remove the employee from the site and initiate the disciplinary process. The contractor shall investigate any violation of a Life-Saving Rule and initiate the disciplinary process within five (5) working days of the violation. The contractor shall furnish Eskom with a copy of the sanction after the disciplinary process.

3.10 SUBSTANCE ABUSE

1. Alcohol and substance abuse are serious threats to any business, especially when it comes to workplace accidents and car driving. As a result, Eskom has the right to take reasonable procedures to identify and prohibit drunk people from entering the company.
2. General Safety Regulation 2A specifies the legal position on intoxication.

Public

When downloaded from the document management system, this document is uncontrolled and the responsibility rests with the user to ensure it is in line with the authorised version on the system.

No part of this document may be reproduced without the expressed consent of the copyright holder, Eskom Holdings SOC Ltd, Reg No 2002/015527/30.

	GENERATION COAL FIRED STATIONS OHS SPECIFICATION FOR Supply and delivery of Dust Handling Plant Auxiliary spares (DHP) at Matimba Power Station for a period of 60 months on an as and when required basis.	Template Identifier	32-726- 03T	Rev	1
		Document Identifier	E2987GX LPMAT	Rev	1
		Effective Date	April 2022		

3. The allowable alcohol and drug level is 0%.
4. All contractors must follow Eskom's procedure 32-37 ("Substance Abuse Procedure"), taking into account that this is an Eskom Life-saving Rule number 4: (BE SOBER), and anyone entering the Eskom site will be subjected to ad hoc alcohol testing if the BU has self-alcohol testing equipment.
5. Contractors are invited to develop their own manual and test their own employees for alcohol on a regular basis.
6. Test results must be marked "Confidential" and kept in the employee's personal file.
7. Eskom's life-saving rules must be included in the induction process.
8. All employees involved in the scope of work must sign the Life-saving rule pledge before commencement of work.

3.11 CONTRACTOR ORGANISATIONAL STRUCTURE

3.11.1 Main Contractor Organogram

The Main contractor must provide an organisational organogram on the company's letter head related to this contract, depicting all the levels of responsibility from the CE down to the supervisors responsible for the contract. List the relevant positions held, names of appointees, legal appointments and the Organogram must be signed off by the company's 16(1) or 16 (2).

The Main contractor must ensure that all appointed contractors comply with this requirement. The Main contractor is responsible for keeping copies of all the organograms' as well as submitting them with the OHS plan. All organograms shall be updated timeously when appointments are changed.

This diagram must be kept up to date and filed in the contract OHS files.

3.11.2 Appointed Contractor/s Organogram

1. Appointed contractors are required to compile their company organogram for the contract on the company's letter head, listing the reporting structure from their CE down to their contract supervisors. The diagram must list the names, positions held, any appointments made and must be signed off by the company's 16(1) or 16 (2).
2. This diagram must be kept up to date, a copy of which must be given to the Main contractor and a copy filed in the relevant contract OHS files.
3. This diagram must be kept up to date and filed in the contract OHS files.

3.12 ROLES AND RESPONSIBILITIES

Commitment

Visible commitment is essential to providing a safe work environment. Managers, supervisors and employees at all levels must demonstrate their commitment by being proactively involved in the day to day operations, in particular the Occupational Health and Safety aspects of any contract / contract.

Public

When downloaded from the document management system, this document is uncontrolled and the responsibility rests with the user to ensure it is in line with the authorised version on the system.

No part of this document may be reproduced without the expressed consent of the copyright holder, Eskom Holdings SOC Ltd, Reg No 2002/015527/30.

	GENERATION COAL FIRED STATIONS OHS SPECIFICATION FOR Supply and delivery of Dust Handling Plant Auxiliary spares (DHP) at Matimba Power Station for a period of 60 months on an as and when required basis.	Template Identifier	32-726-03T	Rev	1
		Document Identifier	E2987GX LPMAT	Rev	1
		Effective Date	April 2022		

Legislation requires that each employee must take reasonable care of themselves and their fellow workers, from management level down to the lowest employee level.

3.12.1 Main contractors and appointed contractors

Note 1: Most of the roles and responsibilities listed apply to both Main contractors and any appointed contractors. Where some of the listed do not apply to both, then the specific responsibilities will be listed and titled. The contractors shall:

1. Carry out all duties as listed in section 8, 9 and 10, the various other regulations that form part of the OHS Act and Regulation 7 of the Construction Regulations.
2. Carry accountability and responsibility for the safety and health of their employees and their appointed contractors within their working area, as contemplated by section 37(2) of the OHS Act;
3. Shall keep a record of all employees including the appointed contractor employees, including date of induction, relevant skills and licenses and be able to produce this list at the request of the Eskom Contract Manager.
4. Ensure that all their appointees are made aware of their accountabilities and responsibilities in terms of their appointment and that they advise and assist these appointees in the execution of their duties.
5. Ensure that the minimum legislative, regulatory and Eskom OHS requirements are complied with on all work sites.
6. Give the Eskom contract managers and line managers / responsible managers their full participation and cooperation.
7. Compile a OHS (Occupational health and safety) file where all relevant health and safety records must be kept for each work site.
8. The Main contractor must provide the contract manager with the Compensation Commissioner's valid letter of good standing before the commencement of work and any future renewal letters obtained during the contract for record-keeping purposes. The letter of good standing shall reflect the name of the contractor's company. Similarly, the Main contractor must provide the Eskom contract manager with all the valid letters of good standing from their appointed contractors.
9. Contractors must provide the Main contractor with a certified copy of the Compensation Commissioner's valid letter of good standing before the commencement of work and any future renewal letters obtained during the contract for record-keeping purposes. The letter of good standing shall reflect the name of the contractor's company.
10. Appoint competent staff to perform the contract work and ensure that all employees are trained in the health and safety aspects relating to such work and that the employees understand the hazards associated with all other work being carried out on the contract.
11. Ensure that all employees are conversant with all relevant work procedures and that they adhere to such procedures. Similarly (without removing the appointed contractors' responsibilities), ensure that their appointed contractors and their employees are conversant with all relevant work procedures and that they adhere to such procedures.
12. Co-ordinate the activities of all the appointed contractors in the interests of safety and health;
13. Ensure that their contractors (whom they intend appointing) have made detailed provision for the cost of safety and health measures throughout the contract.
14. Stop his /her employees and any appointed contractors if such work poses a threat to the health and safety of persons or a risk of degradation to the environment.
15. Take reasonable steps to ensure cooperation between all their appointed contractors.

Public

When downloaded from the document management system, this document is uncontrolled and the responsibility rests with the user to ensure it is in line with the authorised version on the system.

No part of this document may be reproduced without the expressed consent of the copyright holder, Eskom Holdings SOC Ltd, Reg No 2002/015527/30.

	GENERATION COAL FIRED STATIONS OHS SPECIFICATION FOR Supply and delivery of Dust Handling Plant Auxiliary spares (DHP) at Matimba Power Station for a period of 60 months on an as and when required basis.	Template Identifier	32-726-03T	Rev	1
		Document Identifier	E2987GX LPMAT	Rev	1
		Effective Date	April 2022		

16. Ensure that Eskom OHS requirements are communicated to the appointed contractors, evaluate, and assess the appointed contractors OHS files. Only appoint contractors who are competent to do work, have satisfied the OHS compliance requirements and satisfied that the contractor has the necessary competencies and resources to perform the work safely.
17. Appoint full-time competent employees in writing to supervise the performance of all specified work throughout the contract period.
18. Ensure that the supervisor or manager do not supervise work on any site other than the site for which such supervisor has been appointed for.
19. Not victimise or dismiss employees, by virtue of the employee's divulging health and safety information or suspecting such information has been divulged, in the interests of health and safety requirements.
20. Follow a process of disciplinary action if any of their employees or their appointed contractor employees have transgressed any of the requirements of the health and safety specification, safety and health plans, site rules or any other requirements.
21. Before the commencement of work, review the submitted baseline risk assessments to include site or emerging risks. This should be done by a competent person appointed in writing with a view to identify hazardous and potentially hazardous work operations.
22. Ensure that pre-task risk assessments are conducted and documented daily and prior to the starting of any new task, irrespective of whether it is a repetitive task or not.
23. Must ensure that an organisation medical surveillance programme for the duration of the contract is in place and maintained.
24. Prior to having pre-employment and periodic medicals fitness examinations conducted, person/man job specifications must be compiled and handed to the occupational health practitioner.
25. Issue risk-based personal protective equipment (PPE) as a measure of last resort to their employees, inspect such equipment regularly and ensure recipients of PPE are trained in the proper use, care and where necessary, the maintenance of PPE;
Note: should the Main contractor or his/her appointed contractors entertain visitors on site, they will be held responsible for the provision and wearing PPE.
26. Must have a substance abuse program which must be in line with Eskom requirements.
27. Ensure that all incidents are reported and investigated timeously by competent incident investigators as and aligned with 32-95 requirements.
28. Be involved in all of their appointed contractor's incident investigations.
29. When appointing contractors, advise the contract manager in writing timeously and obtain his/her approval prior to them commencing work.

3.12.2 Contractor site supervisor

The contractor site supervisor must be trained in the following:

HIRA, Incident investigation training, Supervisor training, authorised person & PSR, Legal liability

Must:

1. Be competent to perform the required supervisory tasks;
2. Ensure their employees and all appointed contractors comply with the required statutory and Eskom contract requirements;
3. Inspect all work done by the contractors to ensure adherence to Eskom's standards and specifications

Public

When downloaded from the document management system, this document is uncontrolled and the responsibility rests with the user to ensure it is in line with the authorised version on the system.

No part of this document may be reproduced without the expressed consent of the copyright holder, Eskom Holdings SOC Ltd, Reg No 2002/015527/30.

	GENERATION COAL FIRED STATIONS OHS SPECIFICATION FOR Supply and delivery of Dust Handling Plant Auxiliary spares (DHP) at Matimba Power Station for a period of 60 months on an as and when required basis.	Template Identifier	32-726- 03T	Rev	1
		Document Identifier	E2987GX LPMAT	Rev	1
		Effective Date	April 2022		

4. Conduct follow-up inspections to ensure findings are closed out and preventative action is in place.
5. Monitor contractors for adhere to statutory requirements and safety standards.
6. Monitor contractors overall OHS performance on site in order to achieve excellent results
7. Discuss all OHS related problems with the relevant contractor management timeously in the first instance and thereafter the Eskom contract manager in the second instance relating to procedure requirements, non-conformances identified, corrective actions, audits and inspection schedules.
8. Continual liaison between the Main contractor, appointed contractors and employees.
9. Ensures that employees and appointed contractors are aware of latest standards, procedures, work instructions and safety regulations issued by Eskom:
10. Conduct site Inspections for compliance to OHS requirements and compiles the relevant inspection reports.
11. Submit the observation reports to the relevant management.
12. Submit the required OHS reports communicated by Eskom e.g., manpower numbers, incident statistics report etc
13. Have meaningful participation in the contract statutory health and safety committee meetings.
14. Participate in all appointed contractor incident investigations.
15. Participate in the Main contractor's emergency preparedness planning.
16. Ensure that their own employees and those of any appointed contractor are competent to perform the tasks assigned.
17. Issue site instructions on behalf of the Main contractor where and when the appointed contractors deviate from safety requirements.

3.12.3 Contractor Health and Safety officer Parttime or as when required

The contractor health and Safety officer must be trained in the following:

Table 1: The following serves as a guideline for competency requirements.

Medium risk work (short term)
• Part time Safety Officer • Minimum work experience 1yr • Training (risk based)
Low Risk
• Part time Safety Officer • Minimum work experience 1yr

Public

When downloaded from the document management system, this document is uncontrolled and the responsibility rests with the user to ensure it is in line with the authorised version on the system.

No part of this document may be reproduced without the expressed consent of the copyright holder, Eskom Holdings SOC Ltd, Reg No 2002/015527/30.

	GENERATION COAL FIRED STATIONS OHS SPECIFICATION FOR Supply and delivery of Dust Handling Plant Auxiliary spares (DHP) at Matimba Power Station for a period of 60 months on an as and when required basis.	Template Identifier	32-726- 03T	Rev	1
		Document Identifier	E2987GX LPMAT	Rev	1
		Effective Date	April 2022		

- Training (risk based)

Contractor Site Supervisor/Manager

The Contractor site Supervisor must be trained in the following:

- HIRA, Incident investigation training,

3.13 RISK ASSESSMENT (REFER TO 32-520)

It is a legal requirement in terms of Section 8 (2)(d) of the OHS Act for an employer to carry out risk assessments, to establish which risks and hazards are attached to the health and safety of persons due to any work which is performed, any article or substance which is, handled, stored, transported. A risk assessment is defined as an identification of the hazards present in the activity, work, site, and an estimate of the extent of the risks involved, considering whatever precautions are already being taken.

It is essentially a three-stage process:

- identification of all hazards.
- evaluation of the risks;
- Measures to control the risks.

Risk assessments are required to be maintained. This means that significant changes to a process or activity, or any new process or activity should be subjected to a risk assessment and that if new hazards come to light during the work process, then these should also be subjected to risk assessments. Risk assessments for long term processes should be periodically reviewed and updated. Method statements or written safe work procedures are an effective method as information and record of the way jobs / tasks must be performed. Daily or issue based or task specific or on the job risk assessments must be conducted at the place where work is to be performed/ conducted to allow managers and employees to assess any inherent risks that could have been overlooked during the initial risk assessment or any changes that might have occurred in a period of absence. For example if a job / task is extended over a day or halted due to inclement weather.

Guidelines for actual steps involved in a job/task specific risk assessment are:

- Each activity is listed.
- Specific hazards are identified and listed against each activity.
- The magnitude of each risk is rated as Low. Medium or High.

Public

When downloaded from the document management system, this document is uncontrolled and the responsibility rests with the user to ensure it is in line with the authorised version on the system.

No part of this document may be reproduced without the expressed consent of the copyright holder, Eskom Holdings SOC Ltd, Reg No 2002/015527/30.

	GENERATION COAL FIRED STATIONS OHS SPECIFICATION FOR Supply and delivery of Dust Handling Plant Auxiliary spares (DHP) at Matimba Power Station for a period of 60 months on an as and when required basis.	Template Identifier	32-726- 03T	Rev	1
		Document Identifier	E2987GX LPMAT	Rev	1
		Effective Date	April 2022		

- All known documentary and supervisory controls are listed. For instance: What safe work procedures exist for ladders.
- The relevance, effectiveness and sufficiency of these controls are assessed.
- In the event of insufficient or deficient controls for the particular activity, steps to be taken to rectify this shall be recorded, and safe working procedures drawn up.
- Persons responsible for implementing and supervising the task shall be identified, nominated and duly assigned.
- Persons responsible for monitoring the task and carrying out the planned job observation must be nominated.
- Completed risk assessment shall be handed to the Eskom contract manager representative for comment and approval.
- The relevant section of the risk assessment shall be issued with a Transmittal Note to the Supervisor nominated as the responsible person; and the names of workmen who have received instruction on the work content and the sequence of the activities listed in the risk assessment shall be recorded, and their competence established. This instruction shall be done through an interpreter if required and recorded on the Pre-Job Brief (Daily Safe Task Instructions), with reference to applicable Risk Assessments.

3.14 SAFE WORK PROCEDURES / METHOD STATEMENTS

There must be written safe work procedures for all activities, the safe work procedures must be aligned with the risk assessments. Method statements / written safe work procedure are control measures used to prevent an incident from occurring during the execution of the contract. A written safe work procedure/ method statements provide guidance how to execute the task safely. A safe working procedure should be written when: -

- a. Designing a new job or task.
- b. Changing jobs or task;
- c. Introducing new equipment or substances; and

The safe working procedure should identify:

- d. The supervisor for the task or job and the employees who will undertake the task;
- e. The tasks that are to be undertaken that pose risks;
- f. The equipment and substances that are used in these tasks;
- g. The control measures that have been built into these tasks;
- h. Any training or qualification needed to undertake the task;
- i. The personal protective equipment to be worn;
- J. Actions to be undertaken to address safety issues that may arise while undertaking the task.

Public

When downloaded from the document management system, this document is uncontrolled and the responsibility rests with the user to ensure it is in line with the authorised version on the system.

No part of this document may be reproduced without the expressed consent of the copyright holder, Eskom Holdings SOC Ltd, Reg No 2002/015527/30.

	GENERATION COAL FIRED STATIONS OHS SPECIFICATION FOR Supply and delivery of Dust Handling Plant Auxiliary spares (DHP) at Matimba Power Station for a period of 60 months on an as and when required basis.	Template Identifier	32-726- 03T	Rev	1
		Document Identifier	E2987GX LPMAT	Rev	1
		Effective Date	April 2022		

3.15 ROOF WORK (REFER TO 32- 418) (IF APPLICABLE)

Where roof work is to be performed, a risk assessment must be carried out prior to climbing on to the roof to determine the hazards i.e. stability, suitability and strength etc. The consequences of climbing and control measures that are required to be implemented should form part of the risk assessment and the fall protection plan. Should the weather change, the wind velocity must be measured before continuing with roof work.

3.16 FIRE EQUIPMENT AND MAINTENANCE

1. All firefighting equipment's that have been provided shall:
 - a. Be clearly labelled
 - b. Conspicuously numbered
 - c. Entered in a register
 - d. Inspected monthly by a competent person
2. Tested and serviced every 12 months.
3. Results entered in the register and signed by competent person.

3.17 FLAMMABLE AND COMBUSTIBLE LIQUIDS

1. Proposals to store fuel on site must have written approval from the Eskom Contract Manager. The volumes of fuel allowed to be stored will depend on site conditions and Statutory Regulations e.g. by-laws.
2. For storage of hazardous and flammable liquids, a maximum storage as per the scope of work and the approval to be obtained from the local Municipality and to be complied with for the duration the contract.
3. The maximum of 40 litres of fuel is allowed to be stored. Anything greater than 40 litres to be stored in a flammable/combustible liquid store with adequate spillage retention and proper labelling.
4. Adequate numbers of dry chemical fire extinguishers, each with a minimum capacity of 4.5 kg, shall be provided, installed and maintained.
5. All fuel storage areas must comply with the following requirements: -
 - a. Storage should be well clear of buildings.
 - b. Storage areas must be kept free from all combustible materials.
 - c. All Safety signs must be prominently displayed i.e.
 - Flammable Liquid.
 - No Smoking.
 - No open flames.
 - d. Adequate firefighting equipment must be available.
6. Diesel tanks are to be installed in a bunded area; bunded area must be able to contain 110% of tank capacity.

Public

When downloaded from the document management system, this document is uncontrolled and the responsibility rests with the user to ensure it is in line with the authorised version on the system.

No part of this document may be reproduced without the expressed consent of the copyright holder, Eskom Holdings SOC Ltd, Reg No 2002/015527/30.

	GENERATION COAL FIRED STATIONS OHS SPECIFICATION FOR Supply and delivery of Dust Handling Plant Auxiliary spares (DHP) at Matimba Power Station for a period of 60 months on an as and when required basis.	Template Identifier	32-726- 03T	Rev	1
		Document Identifier	E2987GX LPMAT	Rev	1
		Effective Date	April 2022		

7. Bunded area shall be of a concrete or steel construction and lined with a leak proof sealing material.
8. Bunded area shall have a drain valve.
9. No other material/equipment shall be stored in the bunded area.
10. For storage of hazardous and flammable liquids, the approval must be obtained from the Fire department and/or the Municipality (if the services are rendered/available in the local Municipality).
11. The storage of flammable or hazardous storage must be well ventilated.
12. The appropriate Jerry cans designed for petrol/diesel shall be used to store petrol on Eskom sites and the appropriate colour coding should be complied with.

3.17.1 Refuelling at Eskom sites

Before a machine/vehicle can be refuelled, the motor must be stopped. Refuelling shall take place at designated safe areas and appropriate warning signs installed. Suitable drip trays must be used to prevent spillage at the filling nozzle.

3.18 FIRST AID AND EQUIPMENT

1. The requirements of the OHS Act GSR 3 must be observed.
2. First aid appointments must be made to meet the legal requirements. Appointees must be trained to level 2 and the training service provider must be registered in accordance with section 26(1) of the Skills Development Amendment Act, Act No. 37 of 2008. It is good practice for all employees to be trained to at least level 1.
3. When appointing employees for work sites, cognisance must be taken into account the type of work performed, the distance teams are working apart and the terrain to be covered if an emergency should arise.
4. A list of emergency numbers must be displayed on the notice boards and made accessible for all employees.
5. Main Contractor must ensure that his /her employees and appointed contractor employees are familiar with the emergency numbers.
6. Contractors shall have one first aid box for the first 5 persons and thereafter one for every 50 or team of workers on site or part thereof, taking into account the type of work performed and the distance between teams.
7. More first aid boxes shall be provided in accordance with the risk assessment. Boxes must be available and accessible for the immediate treatment of injured persons at the workplace.
8. For offices, signs indicating where the first aid box or boxes are kept as well as the name and contact details of the First Aider of such first aid box or boxes shall be erected.
9. The Main Contractor and appointed contractor shall ensure that alternative arrangements be made for incidents occurring after working hours.

Public

When downloaded from the document management system, this document is uncontrolled and the responsibility rests with the user to ensure it is in line with the authorised version on the system.

No part of this document may be reproduced without the expressed consent of the copyright holder, Eskom Holdings SOC Ltd, Reg No 2002/015527/30.

	GENERATION COAL FIRED STATIONS OHS SPECIFICATION FOR Supply and delivery of Dust Handling Plant Auxiliary spares (DHP) at Matimba Power Station for a period of 60 months on an as and when required basis.	Template Identifier	32-726- 03T	Rev	1
		Document Identifier	E2987GX LPMAT	Rev	1
		Effective Date	April 2022		

3.18.1 Boxes and equipment

The following is a list of minimum contents of a first aid box:

- Item 1: Wound cleaner/antiseptic (100ml).
- Item 2: Swabs for cleaning wounds.
- Item 3: Cotton wool for padding (100 g).
- Item 4: Sterile gauze (minimum quantity 10).
- Item 5: 1 Pair of forceps (for splinters).
- Item 6: 1 Pair of scissors (minimum size 100 mm).
- Item 7: 1 Set of safety pins.
- Item 8: 4 Triangular bandages.
- Item 9: 4 Roller bandages (75 mm X 5 m).
- Item 10: 4 Roller bandages (100 mm X 5 m).
- Item 11: 1 Roll of elastic adhesive (25 mm X 3 m).
- Item 12: 1 Non-allergenic adhesive strip (25 mm X 3 m).
- Item 13: 1 Packet of adhesive dressing strips (minimum quantity, 10 assorted sizes).
- Item 14: 4 First aid dressings (75 mm X 100 mm).
- Item 15: 4 First aid dressings (150 mm x 200 mm).
- Item 16: 2 Straight splints.
- Item 17: 2 Pairs large and 2 pairs medium disposable latex gloves.
- Item 18: 2 CPR mouth pieces or similar devices.

A content check list must be available with all boxes and boxes shall be checked on a regular basis, kept clean and dust free.

3.19 OHS COMMUNICATION SYSTEMS

1. Main Contractor/s and their appointed contractors must develop a communication strategy outlining how they intend to communicate OHS issues to their staff, the mediums they will employ and how they will measure the effectiveness of their OHS communication. Below is a brief on how communication should take place. Where contract meetings are conducted on site, OHS shall be included as a standing agenda point and minutes of these meetings shall be available on site at all times. Minutes of meeting must be compiled and filed in the relevant OHS files. All employees shall have access to these minutes. Attendance register shall be kept for all the health and safety meetings.

3.19.1 Statutory Health and Safety Committees

1. The Main contractor shall establish statutory health and safety committee in terms of Section 19 of the OHS Act. Similarly, appointed contractors shall establish their own statutory health and safety committee.
2. All appointed contractors shall be members of the Main contractor's safety committee.
3. The Committee shall meet to discuss OHS issues concerning the current work being performed, training, upcoming work and OHS requirements, incidents and lessons learned specific OHS problems, safety performance, action plans and other relevant OHS issues. Listed below is a preferred agenda.
4. OHS representatives for a workplace shall be members of the relevant workplace safety committees (Refer to Section 19 (2) (a) of the OHS Act).

Public

When downloaded from the document management system, this document is uncontrolled and the responsibility rests with the user to ensure it is in line with the authorised version on the system.

No part of this document may be reproduced without the expressed consent of the copyright holder, Eskom Holdings SOC Ltd, Reg No 2002/015527/30.

	GENERATION COAL FIRED STATIONS OHS SPECIFICATION FOR Supply and delivery of Dust Handling Plant Auxiliary spares (DHP) at Matimba Power Station for a period of 60 months on an as and when required basis.	Template Identifier	32-726- 03T	Rev	1
		Document Identifier	E2987GX LPMAT	Rev	1
		Effective Date	April 2022		

5. The number of persons nominated by employer must not be more than the Health and Safety Representatives on that specific statutory health and safety committee. (Refer to Section 19(2)(c) of the OHS Act)
6. A statutory health and safety committee meeting shall be held at least 3 monthly (where medium to high risk work is involved, more frequent if required), and all appointed members of the committee shall attend the meeting.
7. Statutory health and safety committees may make recommendations to the Main contractor and the contract manager and the Inspector at DEL.
8. All health and safety committees shall discuss all contracts related OHS Act Section 24 and 25 incidents and other notified serious incidents.
9. Health and safety committees shall follow up on incident investigation recommendations and shall keep record of all recommendations made by the committee.
10. Statutory health and safety committees may make recommendations for the revision of current standards, procedures and practices.
11. The Main contractor and appointed contractors shall ensure that statutory and non-statutory health and safety committees carry out their duties.
12. The chairperson of the health and safety committees shall be selected and appointed by the contractor. The appointed chairperson must be competent to chair meetings and be able to make informed decisions.

3.19.2 Non-statutory health and safety committees

1. Where there are large worksites, then non-statutory sub-committee must be established within that worksite to assist with the communication of health and safety related matters between the statutory health and safety committee and the workplace.
2. The duties and responsibilities of the non- statutory health and safety committees will be the same as the statutory safety committee

3.19.2.1 Agenda

1. The following serves as the guideline for the OHS Committee meeting agenda.
 - List of agenda items:
 - Matters arising from previous minutes
 - Matters arising from Contractor's OHS meetings.
 - Covid-19 compliance
 - Audit results and feedback
 - Review Health and Safety Representative Inspection Reports
 - Review
 - Incident investigation reports
 - Non-Conformances
 - Announcements (near miss/injury/damage)
 - Follow up on recommendations made by the employer in incident investigation reports

Public

When downloaded from the document management system, this document is uncontrolled and the responsibility rests with the user to ensure it is in line with the authorised version on the system.

No part of this document may be reproduced without the expressed consent of the copyright holder, Eskom Holdings SOC Ltd, Reg No 2002/015527/30.

	GENERATION COAL FIRED STATIONS OHS SPECIFICATION FOR Supply and delivery of Dust Handling Plant Auxiliary spares (DHP) at Matimba Power Station for a period of 60 months on an as and when required basis.	Template Identifier	32-726- 03T	Rev	1
		Document Identifier	E2987GX LPMAT	Rev	1
		Effective Date	April 2022		

- Accident Prevention – Safety Promotion
 - Planned Job Observations
 - OHS Training
 - Protective clothing and equipment
 - Incident Announcements / Recall
- Forthcoming High hazard activities.
- Non-conformances.
- Housekeeping.
- Work permits.
- Work procedures.
- Hazardous materials / substances.
- Fire Prevention
- Occupational Hygiene Assessments, Health Risks and Actions
- Security
- Rules, Instructions
- Public Safety
- Environmental Management
- Emergency Preparedness
- Statistics report
- Closure

3.19.2.2 Minutes and action items for all health and safety committee meetings

1. Minutes and record of action items shall be kept of all health and safety committee meetings.
2. Action column with target dates and responsible person shall be clearly visible on the minutes and shall be completed during the meeting.
3. Statutory health and safety committee meeting minutes and record of action items shall be kept for the duration of the contract or a minimum period of three years.
4. Non-statutory health and safety committee meeting minutes shall be kept for the duration of the contract or a minimum period of 12 months.
5. All other meeting minutes where OHS is on the agenda, shall be kept for a minimum period of 12 months.
6. The original copy of the minutes and record of the action items must be signed by the chairperson.
7. The relevant contract manager and Main contractor shall endorse the relevant minutes with his/her recommendations and return the minutes to the relevant contractors chairperson within 14 calendar days of the meeting.

Public

When downloaded from the document management system, this document is uncontrolled and the responsibility rests with the user to ensure it is in line with the authorised version on the system.

No part of this document may be reproduced without the expressed consent of the copyright holder, Eskom Holdings SOC Ltd, Reg No 2002/015527/30.

	GENERATION COAL FIRED STATIONS OHS SPECIFICATION FOR Supply and delivery of Dust Handling Plant Auxiliary spares (DHP) at Matimba Power Station for a period of 60 months on an as and when required basis.	Template Identifier	32-726-03T	Rev	1
		Document Identifier	E2987GX LPMAT	Rev	1
		Effective Date	April 2022		

3.20 TOOL BOX TALKS / DAILY TEAM TALKS / PRE JOB MEETINGS

1. A meeting must be held prior to the commencement of the day's work with all relevant personnel associated with the work task in attendance. The job, relevant procedures, associated hazards, safety measures, i.e. the task risk assessments shall be discussed. Each employee who attends the briefing shall sign an attendance list of that pre-job brief form undertaking that they have an understanding of the tasks, risks and control measures required.
2. Where possible, tool box talks can be included in the pre-job brief meetings. If this does not occur, then weekly tool box talks must be conducted. The toolbox talk topics will be based on OHS issues pertaining to the contract site. The topic and the contents shall be in writing. Attendance registers with the topic listed shall be kept.

3.21 OHS TRAINING

1. The Main contractor, when making a bid for this contract shall provide a breakdown list of the OHS training requirements and the costing of such requirements. Similarly, appointed contractor must provide the same requirements when bidding with the Main contractor.
2. The scope of training includes but is not limited to the type of work being performed and the relevant procedures. Additional to the requirements, will be that the Main contractor and appointed contractors must have the appropriate qualifications, certificates and employees should always be under competent supervision.
3. Where legislative and Eskom recommended appointments are made, the relevant training shall be given to those appointees prior to the acceptance of those appointments.
4. When there is an amendment to the Acts and/or to the regulations, OHS specification and OHS plan, all affected staff shall undergo the applicable refresher training.
5. Appropriate time must be set aside for training (induction and other) of all employees.
6. Records of all training and qualifications of all contractor employees must be kept on the OHS file.

3.21.1 Main Contractor Induction training

The contractor is required to induct its employees and make arrangements with the Business Unit for its employees to attend induction in order to be granted permission to access site. Company and Client induction shall be renewed annually

1. The Main contractor shall ensure that all his / her employees, appointed contractors and their employees have undergone the Eskom OHS induction training prior to commencing work on site.
2. Attendance registers must be completed of any induction training given, which must indicate that they have received and understood the induction training.

Public

When downloaded from the document management system, this document is uncontrolled and the responsibility rests with the user to ensure it is in line with the authorised version on the system.

No part of this document may be reproduced without the expressed consent of the copyright holder, Eskom Holdings SOC Ltd, Reg No 2002/015527/30.

	GENERATION COAL FIRED STATIONS OHS SPECIFICATION FOR Supply and delivery of Dust Handling Plant Auxiliary spares (DHP) at Matimba Power Station for a period of 60 months on an as and when required basis.	Template Identifier	32-726-03T	Rev	1
		Document Identifier	E2987GX LPMAT	Rev	1
		Effective Date	April 2022		

3. Prior to attending the induction training, all employees must undergo a pre-employment medical examination and found fit for duty. A copy of the certificate of fitness must be kept in the OHS file on site for the duration of the contract.
4. All employees and visitors on site shall carry the proof of induction training.
5. It is the contractors responsibility to keep records of induction training.

3.21.2 Appointed Contractor induction training

The Main contractor shall ensure that all his / her employees and appointed contractor employees undergo site specific work induction with regard to the approved contract OHS plan, hazards prevalent on the work site, scope specific risk assessment, rules and regulations, and other related aspects. The induction training should also include identification of sensitive features such as wetlands/vlei areas, red data species, graves, etc.

3.21.3 Visitors to site induction

1. Visitors to the site shall be required to undergo and comply with the Eskom site-specific safety induction prior to being allowed access to site.
2. All visitors must remain in the care and custody of a person (host) who has been properly inducted. No visitors are permitted to undertake any work onsite, of any nature.
3. Visitors who have completed site induction must be provided with a record of proof of Induction training.

3.22 GENERAL TRAINING

The Main contractor will be required to ensure that before an employee commences work on the contract/site, the respective supervisor informs the employee of his scope of authority, the hazards associated with work as well as the control measures to be taken. This will include man-job specifications, the discussion of any task procedures or hazardous operational procedures to be performed by the employee. The Main Contractor is to ensure that the supervisor has satisfied himself that the employee understands the hazards associated with the work to be performed by conducting task/job observations.

3.23 CONTRACTOR SITE ESTABLISHMENT

3.23.1 WHERE CONTRACTORS ARE PROVIDING THEIR OWN FACILITIES, THE FOLLOWING SHALL APPLY:

1. Prior to establishing a contract site, a site plan is required to be drawn and submitted to the contract manager, listing position of all buildings, amenities, storage, stacking areas and temporary electrical installations. The appropriate colour coding and demarcation of storage and stacking areas must be carried out.
2. When compiling the site plan, cognisance must be taken to the establishment of the site camp, ablution facilities and dining area in relation to one another and away from stacking and storage areas.

Public

When downloaded from the document management system, this document is uncontrolled and the responsibility rests with the user to ensure it is in line with the authorised version on the system.

No part of this document may be reproduced without the expressed consent of the copyright holder, Eskom Holdings SOC Ltd, Reg No 2002/015527/30.

	GENERATION COAL FIRED STATIONS OHS SPECIFICATION FOR Supply and delivery of Dust Handling Plant Auxiliary spares (DHP) at Matimba Power Station for a period of 60 months on an as and when required basis.	Template Identifier	32-726-03T	Rev	1
		Document Identifier	E2987GX LPMAT	Rev	1
		Effective Date	April 2022		

3. Main contractor's site facilities should be managed and kept hygienically clean.
4. Where the materials are stored at the work sites, proper stacking and storage shall be carried out and maintained in good order at all times.
5. The contractor shall during the enquiry make provision for the Occupational Hygiene Surveys costs in the bill of quantities as per the OHS Act and its regulations and inline with the scope of work.

3.23.2 WHERE ESKOM IS MAKING PROVISION OF THE FACILITIES TO THE CONTRACTOR, THE FOLLOWING SHALL APPLY:

1. Prior to handing over the site to the contractor, the client (contract managers/end users) shall together with the contractor management conduct inspections, draft and sign the service level agreement.
2. Main contractors shall manage and keep the allocated Eskom facility hygienically clean at all times.
3. It is the responsibility of the contractor to maintain and keep the facility in a good condition.
4. It is the contractor's responsibility to immediately report to the Eskom contract manager/contract manager the defects incurred.
5. Eskom reserves the right to conduct unannounced site inspections.

3.24 SITE ROADS

1. When planning, sufficient areas must be allocated for parking of vehicles and mobile equipment's as well as roadways for ease of manoeuvrability of these vehicles.
2. Sufficient width roads to be provided and adequate space is to be allowed for large vehicles traversing the sites.

3.25 VEHICLE MANAGEMENT

1. It is the responsibility of the driver to ensure:
 - a. Their passengers wear seat belts whilst the vehicle is in motion.
 - b. Comply with all traffic road rules, safety, direction and speed signs.
 - c. Ensure that vehicle loads are properly secured prior to moving off.
 - d. Ensure that vehicles are not overloaded.
2. No persons maybe transported at the back of the bakkie.
3. Drivers are required to conduct the route risk assessment prior to travelling/driving.
4. No drivers or operators may text, talk on cell phones or two-way radios whilst driving.
5. All drivers shall have a valid medical fitness certificate.
6. The First aid box with valid contents and fire extinguishers must be included in the vehicle, be services annually and inspected monthly. Drivers must be trained on how to use the First aid box and fire extinguishers.

Public

When downloaded from the document management system, this document is uncontrolled and the responsibility rests with the user to ensure it is in line with the authorised version on the system.

No part of this document may be reproduced without the expressed consent of the copyright holder, Eskom Holdings SOC Ltd, Reg No 2002/015527/30.

	GENERATION COAL FIRED STATIONS OHS SPECIFICATION FOR Supply and delivery of Dust Handling Plant Auxiliary spares (DHP) at Matimba Power Station for a period of 60 months on an as and when required basis.	Template Identifier	32-726- 03T	Rev	1
		Document Identifier	E2987GX LPMAT	Rev	1
		Effective Date	April 2022		

7. Two triangles must be included in the vehicle and the emergency number be displayed at the back of the vehicle.
8. Each Contract site that is enclosed by demarcation will have system/ process to manage vehicle access to site.
9. Contractor must maintain their vehicles in a roadworthy condition and a vehicle license must be valid at all times and this is applicable to yellow plant.
10. Drivers of light vehicles must avoid stopping or parking in the vicinity of machines. At least 30 (thirty) meters must be left clear between such a vehicle and such a machine.
11. Contractor vehicles can be subject to inspections by the Client/Agent's representative. Vehicles which are not roadworthy will not be permitted to be used on site.
12. Drivers/operators shall be responsible for the travel-worthiness of all loads conveyed by them. Precautions shall be taken to secure all loads properly. Loads contracting from vehicles shall be securely loaded and in daytime a red flag and during darkness a red light or red reflective material shall be attached to the extreme end of such contracting materials.
13. The vehicle inspection checklist must include but not limited to:
 - Reverse alarm / beeper
 - Yellow reflective tape
 - Mud flaps
 - Fire Extinguisher
 - 2 Triangles
 - First Aid Box
 - Safety belts for every seat
 - No fold-up or jockey seat
 - Tyres
 - License disc
 - Yellow reflective tape that must be fitted at a height of between 250mm and 1.5 metres
 - Speed warning sign (100km/h) at the back of the minibus
 - Driver have a Public Driving Permit

3.26 HOUSEKEEPING AND ORDER

1. All contractors shall maintain a high standard of housekeeping within their sites and vehicles for the duration of the contract/contract.
2. Prompt disposal of waste materials, scrap and rubbish is essential and be stored temporarily in a designated waste area, awaiting disposal.
3. Materials/objects shall not be left unsecured in elevated areas – falling objects may cause serious injuries/fatalities.
4. Nails protruding through timber shall be bent over or removed so as not to cause injury.

Public

When downloaded from the document management system, this document is uncontrolled and the responsibility rests with the user to ensure it is in line with the authorised version on the system.

No part of this document may be reproduced without the expressed consent of the copyright holder, Eskom Holdings SOC Ltd, Reg No 2002/015527/30.

	GENERATION COAL FIRED STATIONS OHS SPECIFICATION FOR Supply and delivery of Dust Handling Plant Auxiliary spares (DHP) at Matimba Power Station for a period of 60 months on an as and when required basis.	Template Identifier	32-726- 03T	Rev	1
		Document Identifier	E2987GX LPMAT	Rev	1
		Effective Date	April 2022		

5. All packaging material including boxes, pallets, crates, etc. to be removed from the work area immediately.
6. On completion of his / her work, the contractor is responsible for clearing his / her work area of all materials, scrap, temporary buildings and building bases to the satisfaction of the client/agent.
7. In cases where an inadequate standard of housekeeping has developed, compromising safety and cleanliness, anyone has the responsibility to bring it to the attention of the Main contractor in the first instance and the Eskom contract/contract manager in the second instance.
8. The Eskom contract/contract manager has the right to instruct the Main contractor and appointed contractors to cease work until the area has been tidied up and made safe. Neither additional costs nor extension of time to the contract shall be allowed as a result of such a stoppage. Failure to comply with this requirement will result into site cleaning by another cleaning contractor company at the cost of the Main contractor.
9. The Main contractor shall carry out regular safety/housekeeping inspections daily to ensure maintenance of satisfactory standards. The Main contractor shall document the results of each inspection and shall maintain records for viewing.

3.27 STACKING AND STORAGE

1. The competent personnel must be appointed in writing to manage and supervise all stacking and storage on site.
2. Before stacking any material, the contractors or their employees must consult the contract manager for authorisation to use such an area for stacking purposes. This is to prevent haphazard arrangements.
3. Adequate care must be taken by the contractor to ensure that storage and stacking is carried out correctly and safely.
4. Correct shelf stacking must be carried out, heavy and bulky on the bottom, light and small on top.

3.28 WORKPLACE SIGNAGE AND COLOUR CODING

1. Symbolic safety signage shall be displayed where it is required by legislation.
2. All symbolic safety signage shall conform to the requirements of SANS standard 1186.
3. Signs shall be positioned to be seen from most positions within the work sites / areas.
4. All signage must be clear at all times and be replaced timeously when worn out.
5. Contractors establishing sites must erect a company sign at their site offices to reflect the name and contact details of the: contractor site/responsible manager; supervisors; Health and Safety Manager/Practitioner; First Aider; Health and Safety Representative and Evacuation warden.
6. The location of every first aid box; fire extinguisher and emergency exit is to be clearly indicated by means of a sign.
7. When using, an explosive power tool the appropriate signage shall be erected, warning people of its use.

Public

When downloaded from the document management system, this document is uncontrolled and the responsibility rests with the user to ensure it is in line with the authorised version on the system.

No part of this document may be reproduced without the expressed consent of the copyright holder, Eskom Holdings SOC Ltd, Reg No 2002/015527/30.

	GENERATION COAL FIRED STATIONS OHS SPECIFICATION FOR Supply and delivery of Dust Handling Plant Auxiliary spares (DHP) at Matimba Power Station for a period of 60 months on an as and when required basis.	Template Identifier	32-726-03T	Rev	1
		Document Identifier	E2987GX LPMAT	Rev	1
		Effective Date	April 2022		

8. Contractors shall provide signage where work is conducted and where unauthorised entry is prohibited and/or where alerting and cautioning passers-by to be aware of potential dangers.
9. The meanings of the appropriate symbolic signage must be discussed during induction training and toolbox talks.
10. Where possible, within workshops, work areas and established premises, the appropriate sign indicating the meaning of symbolic safety signs must be displayed.

3.29 TOOLS AND EQUIPMENT

1. Contractors shall ensure that all tools and equipment are identified, safe to be used and is maintained in a good condition.
2. Contractors shall ensure that all tools and equipment are listed on an inventory list, be regularly inspected at least monthly or as required by legislation and risk assessments. The equipment should be numbered or tagged so that it can be properly monitored and inspected.
3. Where applicable, tools and equipment must have the necessary approved test or calibration documentation prior to being brought onto the contract and the records shall form part of the OHS plan. Maintenance calibration shall be undertaken in terms of the manufacturer's requirements.
4. All fuel driven equipment must be properly maintained in accordance with the manufacturer's recommendations and legal requirements.
5. Eskom reserves the right to inspect tools or items of equipment brought to site by contractors for use on this contract.
6. Should Eskom personnel find any item that is inadequate, faulty, unsafe or in any other way unsuitable for the safe and satisfactory execution of the work for which it is intended, the Eskom personnel shall advise the contractor in writing and the contractor shall forthwith remove the item from site and replace it with a safe and adequate substitute.

Note: In such cases, the contractor shall not be entitled to extra payments or extensions of time in respect of delay caused by Eskom's instructions.

7. Where defective tools and equipment's are identified, such tools and equipment shall be removed out of site immediately, locked away to prevent further use until such time as the tool or piece of equipment has been repaired.
8. Contractors shall ensure that the appropriate records are kept for all tools and equipment used on the contract. Such tools and equipment's shall be subjected to regular inspections.

3.29.1 Hand tools

1. All hand tools (hammers, chisels, spanners, etc.) must be recorded on a register and inspected by the construction supervisor on a monthly basis as well as by users prior to use.
2. Under no circumstance will the contractors be allowed to use their equipment's with mushroom heads, to be removed at the end or beginning of shift prior to use.
3. Tools with sharp points in toolboxes must be protected with a cover.
4. All files and similar tools must be fitted with handles.

Public

When downloaded from the document management system, this document is uncontrolled and the responsibility rests with the user to ensure it is in line with the authorised version on the system.

No part of this document may be reproduced without the expressed consent of the copyright holder, Eskom Holdings SOC Ltd, Reg No 2002/015527/30.

	GENERATION COAL FIRED STATIONS OHS SPECIFICATION FOR Supply and delivery of Dust Handling Plant Auxiliary spares (DHP) at Matimba Power Station for a period of 60 months on an as and when required basis.	Template Identifier	32-726- 03T	Rev	1
		Document Identifier	E2987GX LPMAT	Rev	1
		Effective Date	April 2022		

5. No make shift tools are permissible on the contract.

3.30 LADDERS

1. Ladders used shall conform to the requirements of GSR 13A and used in terms of GSR 6.
2. The appropriate head protection, with chin strap shall be worn by employees working from a ladder or with climbing irons.
3. The ladder wheels, brakes and platform must be in good condition.
4. All metal parts to be in good condition, no cracks.
5. The appropriate head protection, with chin strap shall be worn by employees working from a ladder or with climbing irons.
6. Non-slip devices must be in good condition and no paint to be on wooden ladders
7. Climbing irons are permitted to be used in place of ladders on condition that the requirements of GSR 6 are not compromised and from an electrical point of view not damage any cabling. The working at heights risk assessment must indicate the use of climbing irons.
8. Employees using climbing irons shall be suitably trained in the use, care and maintenance of such climbing irons.
9. When using climbing irons, the appropriate rope grab fall prevention system shall be used.
10. The correct fall protection equipment shall be worn and used whilst climbing up, working from and climbing down ladders.
11. The appropriate head protection, with chin strap shall be worn by employees working from a ladder (risk based) or with climbing irons.
12. A detailed inspection of all ladders shall be conducted monthly by a competent person and every time prior to climbing by employees using such ladders. The inspection check lists must be filed in the site OHS files

3.31 SCAFFOLDING (IF APPLICABLE)

1. Scaffolding use shall conform to the requirements of Eskom procedure 32-418 and used in terms of GSR 6.
2. The requirements for using a scaffold platform shall be determined by the work at heights risk assessment.
3. All scaffolding that will be used shall conform to the SANS standard 10085.
4. Scaffolding shall be erected and inspected by the competent personnel.
5. The appropriate training for scaffold users shall be conducted prior to climbing on to the scaffold.
6. The correct fall protection equipment shall be worn and used whilst climbing up, working from and climbing down the scaffolds as the risk assessment.

Public

When downloaded from the document management system, this document is uncontrolled and the responsibility rests with the user to ensure it is in line with the authorised version on the system.

No part of this document may be reproduced without the expressed consent of the copyright holder, Eskom Holdings SOC Ltd, Reg No 2002/015527/30.

	GENERATION COAL FIRED STATIONS OHS SPECIFICATION FOR Supply and delivery of Dust Handling Plant Auxiliary spares (DHP) at Matimba Power Station for a period of 60 months on an as and when required basis.	Template Identifier	32-726-03T	Rev	1
		Document Identifier	E2987GX LPMAT	Rev	1
		Effective Date	April 2022		

7. A detailed inspection of all scaffolding shall be conducted at suitable intervals not exceeding seven days by a competent person and visual inspection shall be done every time prior to climbing by employees using such scaffolding. The inspection check lists must be filed in the site OHS files.
8. Visual inspections must always be carried out prior to every use.

3.32 AUDITING

3.32.1 Approval and compliance of Main contractor OHS plan

The Contractor's OHS Plan will be audited against compliance checklist so as to verify compliance to the requirements of the Eskom OHS specifications. Once there is compliance only then will the Main contractors OHS plan be approved by the contract manager or an appointed Eskom contract custodian. The implementation of the OHS Plan shall be assessed / audited by Eskom personnel on a regular basis. This will include physical conditions evaluation.

3.32.2 Eskom OHS audits

Eskom shall evaluate all contractors' OHS performance on an ongoing basis against the legal, Eskom requirements, OHS specification and the contractors OHS plans.

Note: Eskom reserves the right to conduct unannounced audits on contractors

There will be quarterly audits conducted by Eskom on the Main contractor/s and/or appointed contractors. These audits shall be attended by the contractor's site manager or his representative. Audit report will be issued within 14 days after the audit. Contractors to submit action plan within 7 days after receiving audit report to Matimba Safety department.

If there are any findings / non-compliance identified as serious in these audits, an activity will be stopped for that specific Main Contractor and appointed contractor. Refer to section on "Work Stoppage" in this OHS Specification.

Internal Audits must be conducted as follows:

- High risk: Every 3 months, however, OHS inspections shall be conducted on a monthly basis.
- Construction activities as per Construction Regulations
- **Medium risk: Every 6 months (twice a year), however regular OHS inspections shall be conducted.**
- Low risk: Every 12 months (once a year), however regular OHS inspections shall be conducted.

3.32.3 Contractor audits

Main Contractors are required to conduct internal audits on both their employees and their appointed contractors on the implementation of their OHS Plan on a monthly basis or when the scope of work changes. A summary of the findings and the proposed corrective actions shall be submitted to Eskom contract manager within one week after completion of the audit. Where appointed contractors are

Public

When downloaded from the document management system, this document is uncontrolled and the responsibility rests with the user to ensure it is in line with the authorised version on the system.

No part of this document may be reproduced without the expressed consent of the copyright holder, Eskom Holdings SOC Ltd, Reg No 2002/015527/30.

	GENERATION COAL FIRED STATIONS OHS SPECIFICATION FOR Supply and delivery of Dust Handling Plant Auxiliary spares (DHP) at Matimba Power Station for a period of 60 months on an as and when required basis.	Template Identifier	32-726- 03T	Rev	1
		Document Identifier	E2987GX LPMAT	Rev	1
		Effective Date	April 2022		

audited by the Main contractor a copy of the audit report shall be submitted to the appointed contractor within 7 days of the audit.

3.33 SMOKING

The national smoking policy must be observed and smoking is permitted in designated areas only (Eskom Smoking Procedure 32-36).

3.34 CELLULAR PHONES

The National Road Traffic Act requirements regarding the use of cellular phones must be observed, when driving and or operating mobile equipment and or machinery. The personal use of cell phones in the plant is prohibited unless it is an emergency or for work purpose. The use of cell phone camera in the plant must be in line with the national key point Act and the Plant safety regulation.

3.35 OCCUPATIONAL HEALTH, HYGIENE AND REHABILITATION

All contractors are required to develop an Occupational Health, Hygiene and Rehabilitation program. The program is intended to ensure that the risks to health are identified and controlled.

3.35.1 Medical Assessments

Note: Eskom will only accept medical surveillances conducted by an Occupational Health Practitioner who holds a qualification in occupational health.

1. Main contractors must ensure that their employees and their appointed contractor employees have a medical surveillance program whereby their employees undergo entry, periodic and exit medical fitness examinations.
2. The health risk assessment must be used to compile the man job specification and address the hazards that the employees will be exposed to.
3. For the appropriate medical examinations to be conducted, each employee must have a man job specification, which must indicate the description of work, list of hazards and potential occupational exposure limits, physical hazards and required physical attributes.
4. Medical fitness certificates shall be renewed annually for employees who are working on site. This shall be maintained until completion of the contract.
5. The Main Contractor must ensure that his / her employees and appointed contractor employees have undergone pre-entry medical examination before starting work on the contract.
6. The Main contractor shall provide a documented process for managing those employees who are issued with a conditional certificate of fitness.
7. The contractor shall include in the OHS file the record of the employees exit medical fitness certificates as and when their employees leave the company.

Public

When downloaded from the document management system, this document is uncontrolled and the responsibility rests with the user to ensure it is in line with the authorised version on the system.

No part of this document may be reproduced without the expressed consent of the copyright holder, Eskom Holdings SOC Ltd, Reg No 2002/015527/30.

	GENERATION COAL FIRED STATIONS OHS SPECIFICATION FOR Supply and delivery of Dust Handling Plant Auxiliary spares (DHP) at Matimba Power Station for a period of 60 months on an as and when required basis.	Template Identifier	32-726- 03T	Rev	1
		Document Identifier	E2987GX LPMAT	Rev	1
		Effective Date	April 2022		

3.36 ROLES AND RESPONSIBILITIES

All contractors are required to list employee's roles and responsibilities pertaining to the contract.

3.37 WORKING AT HEIGHTS

3.37.1 General Requirements

Wherever reasonably practicable, preference is given to the performance of work at ground level as opposed to the elevated position. Where work in an elevated position is necessary, preference is given to fall prevention measures such as, but not limited to, effective barricading and the use of work platforms. Persons may only work from a fall risk position if a site-specific fall protection plan developed by the appointed competent person (as per 32-418 procedure) is in place and correctly implemented and consists of the following:

1. All appointments for the fall protection plan developer and implementer are in place.
2. Baseline risk assessment, which is specific and incorporates the working at height risk assessment, as well as the site-specific risk assessment, has been completed for the work to be conducted.
3. Safe working procedure/task analysis and work instructions, approved by a competent person, are in place.
4. A fall rescue plan, along with necessary equipment's and trained rescuers, are in place.
5. Appropriate training, as determined by the risk assessment, has been provided.
6. Appropriate height safety equipment and personal protective equipment have been issued to the individual.
7. There are equipment inspection procedures and up-to-date inspection records.
8. Individuals are medically fit to work at height, and records of this are kept.
9. A site-specific risk assessment is performed.

While work is in progress, adequate warning signs and/or barricades shall be used in all areas where there is a risk of persons being injured by materials or equipment falling from the work area. Barricades should be continuous and easily visible.

A drop zone shall be established with appropriate warning signs and barricading, warning personnel below of workers above and potential falling objects.

Every employer shall ensure that work at height is:

1. properly planned;
2. appropriately supervised; and

Public

When downloaded from the document management system, this document is uncontrolled and the responsibility rests with the user to ensure it is in line with the authorised version on the system.

No part of this document may be reproduced without the expressed consent of the copyright holder, Eskom Holdings SOC Ltd, Reg No 2002/015527/30.

	GENERATION COAL FIRED STATIONS OHS SPECIFICATION FOR Supply and delivery of Dust Handling Plant Auxiliary spares (DHP) at Matimba Power Station for a period of 60 months on an as and when required basis.	Template Identifier	32-726- 03T	Rev	1
		Document Identifier	E2987GX LPMAT	Rev	1
		Effective Date	April 2022		

3. carried out in a manner that is, as far as is reasonably practicable, safe and that its planning includes the selection of work equipment.

3.38 CONFINED SPACES

1. The contractor shall ensure that they comply with the plant safety regulation (240-150642762) in relation to the confined spaces.
2. The contractor must ensure that at least one person or there is a responsible person who is trained on work that will be carried in the confined spaces, also to rescue and conduct the risk assessment.
3. The contractor must ensure that the station rescue emergency number is always available.

3.39 PERSONAL PROTECTIVE EQUIPMENT REQUIREMENTS

1. The Main contractor must provide a detailed programme that includes the issuing, maintenance and replacement of PPE for all his employees and appointed contractors on site.
2. All contractors shall comply with the requirements of GSR 2 of the OHS Act and PPE Specification Standard 240-44175132.
3. The risk based PPE matrix must be compiled detailing the types of PPE that is required to be issued to employees performing the respective tasks.
4. If there are exceptional circumstances in which certain activities necessitate the use of additional PPE, a risk assessment must be done, in which such PPE requirements will be determined and issued.
5. All contractors shall ensure that their visitors wear and use the correct PPE whilst on worksites.
6. Where PPE is required and visitors are not in possession of, then it is the individual contractor's responsibility to provide the PPE.
7. All PPE purchased and used by all contractor employees including visitors must comply with the relevant SANS standards.
8. Where deemed as a requirement (as per risk assessment), then high visibility vests shall be worn.
9. Monthly inspection records of PPE must be kept in the Safety file

Public

When downloaded from the document management system, this document is uncontrolled and the responsibility rests with the user to ensure it is in line with the authorised version on the system.

No part of this document may be reproduced without the expressed consent of the copyright holder, Eskom Holdings SOC Ltd, Reg No 2002/015527/30.

	GENERATION COAL FIRED STATIONS OHS SPECIFICATION FOR Supply and delivery of Dust Handling Plant Auxiliary spares (DHP) at Matimba Power Station for a period of 60 months on an as and when required basis.	Template Identifier	32-726- 03T	Rev	1
		Document Identifier	E2987GX LPMAT	Rev	1
		Effective Date	April 2022		

10. The contractor shall provide training to his/her employees on the correct use, care and maintenance of PPE and keep the record.

3.40 INCIDENT INVESTIGATION

All incidents shall be investigated in terms of OHS Act General Administrative Regulations 8 and 9, using Eskom Procedure 32-95 OHS incident management as a reference, and where injuries as contemplated in sections 24 and 25 have been sustained, be reported to the Department of Employment and Labour.

Contractors shall use its company Flash report to report incidents immediately or before end of shift. The standard General Administrative Regulation Annexure 1 "Recording of an Incident form" for all incident investigation reports. The objective of incident investigation, should not only be a legal requirement, but should establish why and how the incident occurred and find out the real root cause of the incident and to decide on precautionary measures that are required to address the root cause to prevent any further recurrences of the same or similar incidents.

3.40.1 STATISTICAL REPORTING

1. Statistics is an integral part of the framework for measuring health and safety performance and assist in improving the organisation's health and safety performance
2. The principal contractor must report to the Eskom contract responsible manager, by the 1st of every month, their SHE statistics and those of their appointed contractors, specific to the contract.
3. The statistical information required is:
 - Name of the Contractor Company
 - Total number of employees per Principal contractor
 - Actual man-hours worked
 - Days worked
 - Days lost
 - Incident data: Medicals, Fatalities, Lost time, first aid, near misses,
 - Property damage
 - SHE statistical data as per the standard form

Public

When downloaded from the document management system, this document is uncontrolled and the responsibility rests with the user to ensure it is in line with the authorised version on the system.

No part of this document may be reproduced without the expressed consent of the copyright holder, Eskom Holdings SOC Ltd, Reg No 2002/015527/30.

	GENERATION COAL FIRED STATIONS OHS SPECIFICATION FOR Supply and delivery of Dust Handling Plant Auxiliary spares (DHP) at Matimba Power Station for a period of 60 months on an as and when required basis.	Template Identifier	32-726- 03T	Rev	1
		Document Identifier	E2987GX LPMAT	Rev	1
		Effective Date	April 2022		

3.40.2 PLANNED TASK OBSERVATIONS

1. Planned task observations are a critical step in identifying any deviations from specified process and or procedures.
2. Contractors are required to carry out periodic task observations on employees and therefore need to conduct observations as per schedule.
3. Following a task observation, feedback and instruction must be given immediately to the employees who have been observed

3.41 EMERGENCY MANAGEMENT

The art of emergency preparedness and response is to minimise the effects of any emergency and to restore normal activities as soon as possible. The contractor must develop and align their own Emergency response plan with Eskom's to address any emergency which might arise at any given point in time. The contractor to familiarise themselves with the Eskom emergency response plan and procedure. Periodic emergency drills must be undertaken to test the effectiveness of their plan. This must be recorded and provided on request.

3.42 NON-CONFORMANCE AND COMPLIANCE

1. Any non-compliance to any health and safety requirement in this OHS specification is subject to discipline in terms of the Eskom Procurement and Supply Chain Management Procedure.
2. Main contractors are required to implement a non-conformance procedure (if not already in place) for issuing to contractors for transgressions. The procedure can include "quality" related non-conformance issues. Similarly, appointed contractors must implement a non-conformance procedure.
3. The procedure for the issuing and closing off of non-conformance reports shall be strictly adhered to.
4. Contractor contract management must monitor the close out of non-conformances issued, in not doing so; any recommendations made may not be implemented.
5. Where non-conformances are issued by Eskom then one of the close-out steps of the procedure will be for the offender to be called by the responsible contract manager to explain the non-conformance issued and what plan is in place to prevent a recurrence of the non-conformance.
6. Should the contractor fail to provide adequate PPE (as per PPE standards) to their employees for the tasks being performed and/or to visitors; failure to enforce the wearing of such PPE will be viewed as a transgression of the legislative and Eskom requirements.

Public

When downloaded from the document management system, this document is uncontrolled and the responsibility rests with the user to ensure it is in line with the authorised version on the system.

No part of this document may be reproduced without the expressed consent of the copyright holder, Eskom Holdings SOC Ltd, Reg No 2002/015527/30.

	GENERATION COAL FIRED STATIONS OHS SPECIFICATION FOR Supply and delivery of Dust Handling Plant Auxiliary spares (DHP) at Matimba Power Station for a period of 60 months on an as and when required basis.	Template Identifier	32-726- 03T	Rev	1
		Document Identifier	E2987GX LPMAT	Rev	1
		Effective Date	April 2022		

3.43 OHS FILES

1. OHS file means documents or records in permanent form, containing the information about the safety and health management system from inception, execution to completion of works.
2. All contractors are required to keep the OHS file on every contract site. If there is more than one site per contract, a file per site shall be kept at that site. Contractors may keep additional files at their head office as additional records. The OHS file shall be maintained by all the contractors on their contract sites and shall be available on request for audit and inspection purposes.
3. The OHS file shall consist of the OHS documentation/information in line with the OHS requirements/specification, legal and other requirements.
4. The sequence of filing the documentation must be kept in the same sequence as listed in this OHS requirements /specification and the OHS plan.
5. Each record shall be separated by partitions to afford easy identification and access. Each partition must be labelled.
6. On completion of the work/contract, the main contractor must hand over a consolidated health and safety file to the contract manager.
7. In case where the contract is extended, should the documentation in the OHS files become cumbersome, the older documentation must be archived in boxes which shall be correctly labelled and be available for auditing purposes. The archived documentation must be handed over at the completion of the contract.

3.44 WORK STOPPAGE

1. Any person may stop any activity where an unsafe act or unsafe condition that poses or may pose an imminent threat to the safety and health of an individual or create a risk of degradation of the environment. This includes any unauthorised work or service performed by, or legally or contractually non-compliant acts or omissions by, any contractor contracted to work at that site.
2. Work stoppages that are initiated due to OHS concerns, non-compliance, or poor performance related to the contractor's works or services shall not warrant any financial compensation claim lodged against Eskom where the contractor has not met the requirements defined legally or contractually.
3. Where stoppages are carried out, the required non-conformance report shall be raised.
4. All work stoppages ideally should be investigated and documented by contract custodians.

3.45 HOURS OF WORK

The requirements of the Basic Conditions of Employment Act, Chapter Two "Regulation of Working Time" must be adhered to. All contractors are required to maintain an accurate record of time worked by each employee.

Public

When downloaded from the document management system, this document is uncontrolled and the responsibility rests with the user to ensure it is in line with the authorised version on the system.

No part of this document may be reproduced without the expressed consent of the copyright holder, Eskom Holdings SOC Ltd, Reg No 2002/015527/30.

	GENERATION COAL FIRED STATIONS OHS SPECIFICATION FOR Supply and delivery of Dust Handling Plant Auxiliary spares (DHP) at Matimba Power Station for a period of 60 months on an as and when required basis.	Template Identifier	32-726- 03T	Rev	1
		Document Identifier	E2987GX LPMAT	Rev	1
		Effective Date	April 2022		

3.45.1 Normal work

All work conducted on site shall fall within the legal requirements in accordance with the Basic Conditions of Employment Act. Contractors will notify their Eskom Supervisor or contract manager of any work that needs to be performed after hours according to the agreed arrangements. (The application needs to be submitted timeously). Where applicable, the notification should include proof of application, for overtime, to the Department of Employment and Labour and /or the letter of approval from the Department of Employment and Labour.

3.45.2 Night work

When night work is to be performed, the baseline risk assessment must be reviewed to include the management of night work. Contractors shall provide sufficient lighting to enable the entire work site to be illuminated to a degree that employees will not work in dark (un-illuminated) or dimly lit areas. Care must be exercised as not to use few lights with high light intensives as this will cause night blindness.

If work is continuing from day light into night, at dusk, a tool box talk must be held where all employees will be advised of the hazards of night work and the extra precautions which require to be taken, i.e. poor housekeeping, stepping on uneven ground, stepping into holes etc.

3.45.3 Overtime

When overtime is required to be performed, the appointed contractors shall inform the Main contractor of such action. The Main contractor shall inform the Eskom contract manager of such function and provide proof of exemption from the Department of Employment and labour. Contractors shall be aware of the effects of human fatigue and regulate overtime accordingly. The baseline risk assessment must be reviewed to include the management of overtime work.

3.46 OMISSIONS FROM SAFETY AND HEALTH REQUIREMENTS SPECIFICATION

By drawing up this OHS specification Eskom has endeavoured to address the most critical aspects relating to OHS issues in order to assist the contractor to adequately provide for the health and safety of employees on site.

Should Eskom not have addressed all OHS aspects pertaining to the work that is tendered for, the contractor needs to include it in the OHS plan and inform Eskom of such issues when signing the contract.

3.47 CONTRACTOR PERFORMANCE MONITORING

Contractor management is required to do the following as part of the continuous improvement initiatives:

- Visible Felt leadership by top management
- Identify critical tasks and monitor by conducting Job Observations

Public

When downloaded from the document management system, this document is uncontrolled and the responsibility rests with the user to ensure it is in line with the authorised version on the system.

No part of this document may be reproduced without the expressed consent of the copyright holder, Eskom Holdings SOC Ltd, Reg No 2002/015527/30.

	GENERATION COAL FIRED STATIONS OHS SPECIFICATION FOR Supply and delivery of Dust Handling Plant Auxiliary spares (DHP) at Matimba Power Station for a period of 60 months on an as and when required basis.	Template Identifier	32-726- 03T	Rev	1
		Document Identifier	E2987GX LPMAT	Rev	1
		Effective Date	April 2022		

- Contractor Chief Executive or Managing Director shall present the lost time incidents at Business Unit Power Station General Managers meeting

3.48 CONTRACT SIGN OFF

On completion of the contract, all Eskom team must conduct the final audit, inspections, and housekeeping to identify defects, outstanding actions, and open incident cases, and present their findings to the contractor and Eskom contract manager, who must facilitate the closeout. Once the contractor has closed all findings the Eskom's team will verify and sign off prior to issuing a completion certificate and final payment.

3.49 ESKOM'S RIGHT TO TERMINATE THE CONTRACT

The contractor/supplier shall at all times comply with Eskom's occupational health and safety (OHS), legal and other requirements as amended for the duration of the contract. In addition, the contractor shall comply with the requirements contained in the SHE Specification. Eskom reserves the right to terminate the contract in the event that the contractor has built up a history of poor performance or non-conformance in relation to matters of Eskom OHS and legal compliance. No work may commence until the health and safety file has been approved by Eskom OHS personnel.

5. REVISIONS

Date	Rev.	Compiler	Remarks
June 2026	1	Mosale Madisha	This provides the initial OHS specification requirements that must be met by the relevant contractors who have been awarded a contract for the work to be performed for Eskom Generation.

6. DEVELOPMENT TEAM

- Matimba Safety department

Public

When downloaded from the document management system, this document is uncontrolled and the responsibility rests with the user to ensure it is in line with the authorised version on the system.

No part of this document may be reproduced without the expressed consent of the copyright holder, Eskom Holdings SOC Ltd, Reg No 2002/015527/30.