

## **Standard**

Title: Life-Saving Rules Document Identifier: 240-62196227

Alternative Reference N/A

Number:

. .,,

Area of Applicability: Eskom Holdings SOC Ltd

Functional Area: Risk and Sustainability -

OHS

Revision: 7

Total Pages: 12

Next Review Date: February 2030

Disclosure Classification:

**Controlled Disclosure** 

Compiled by

**Functional Responsibility** 

Authorised by

**K Modiole** 

**Senior Advisor - OHS** 

KTModiolo

**Risk and Sustainability** 

Date: 13 February 2025

M Moahlodi

Senior Manager - OHS

**Risk and Sustainability** 

Date: 13 February 2025

pp K Pather

**General Manager** 

Risk and Sustainability

(Dave Lucas)

Date: 17 February 2025

Unique Identifier:

240-62196227

Revision:

Page:

2 of 12

7

# Content

				Page		
1.	Introduction					
2.	Supporting Clauses					
	2.1 Scope					
		•	Purpose			
			Applicability			
		2.1.3	Effective Date	3		
	2.2 Normative/Informative References					
		2.2.1	Normative	4		
		2.2.2	Informative	5		
	2.3 Definitions					
	2.4 Abbreviations					
	2.5 Roles and responsibilities				6	
		2.5.1	Risk and Sustainability OHS Department			
		2.5.2	All Groups/Divisions			
			All employees (Eskom and contractors)			
	2.6 Process for monitoring					
	2.7	Relate	ed/Supporting documents	7		
3.	Document content					
	3.1 Eskom Life-Saving Rules					
		3.1.1	RULE 1: OPEN, ISOLATE, TEST, EARTH AND CREATE AN EQUIPOTENTIAL ZONE BEFORE TOUCH	7		
		3.1.2	RULE 2: HOOK UP AT HEIGHT			
			RULE 3: BUCKLE UP			
			RULE 4: BE SOBER			
		3.1.5	RULE 5: ENSURE THAT YOU HAVE A PERMIT TO WORK	9		
		3.1.6	RULE 6: ENSURE SAFE LIVE WORKING	9		
	3.2	Conse	equences of Violating a Life-Saving Rule	10		
4.	Acc	eptance	e	10		
5.	Revisions10					
6.	Review Team12					
7.	Acknowledgements					

Revision: 7

Page: 3 of 12

# 1. Introduction

Eskom and its subsidiaries will conduct business with respect and duty of care for people to ensure that no operating condition or urgency of service endangers the life of anyone or causes injury, ill-health or damage to the environment. Eskom is committed to preventing all work-related injuries and ill-health. In fulfilling this commitment to protect people, the environment and property, management will provide and maintain a safe and healthy work environment, in accordance with industry standards and compliance with legislative requirements.

At-risk behaviour leads to incidents. Life-saving Rules are safety rules created to enforce zero tolerance for serious at-risk behaviours. These rules have been determined in terms of the consequences of the behaviours they describe, that is, a particular set of behaviours or actions with a high probability of causing disabilities or fatalities when performed.

The Eskom Life-Saving Rules complement our existing health and safety best practices and are safety rules to be followed at all locations.

The Life-Saving Rules apply to all Eskom employees, agents, consultants, and contractors. Visitors to Eskom should also respect and adhere to these rules as applicable and could be instructed to leave the Eskom premises with immediate effect should they refuse to do so.

# 2. Supporting Clauses

# 2.1 Scope

This standard shall apply at all Eskom sites to promote a safe working environment for all Eskom employees, agents, consultants, and contractors. Visitors to Eskom should also respect and adhere to these rules, as applicable.

## 2.1.1 Purpose

This standard clarifies the six most prominent causes of serious injuries, and fatalities within Eskom, and Eskom's intention to enforce "ZERO TOLERANCE" concerning non-adherence to these rules, due to the potential consequences of serious injury or fatality at the workplace.

# 2.1.2 Applicability

This standard shall apply throughout Eskom Holdings SOC Limited, its divisions, subsidiaries, and entities wherein Eskom has a controlling interest and/or Eskom contractors unless specifically exempted by Risk and Sustainability, where the business transacted may be completely different to the core business of Eskom.

## 2.1.3 Effective Date

This document will be effective from the date of authorisation.

Revision: 7

Page: 4 of 12

#### 2.2 Normative/Informative References

Parties using this document shall apply the most recent edition of the documents listed in the following paragraphs.

**Note:** The documents listed below are not an exhaustive list of Eskom policies, procedures, standards, work instructions, safe work procedures and method statements that are utilised when performing work.

#### 2.2.1 Normative

- [1] Occupational Health and Safety Act 85 of 1993.
- [2] ISO 9001 Quality Management Systems.
- [3] ISO 45001 Occupational Health and Safety Management Systems Requirements.
- [4] 32-37 Substance Abuse Procedure.
- [5] 32-95 Environmental, Occupational Health and Safety Incident Management Procedure.
- [6] 32-136 Contractor Health and Safety Requirements.
- [7] 32-345 Eskom Vehicle Safety Specification.
- [8] 32-407 Behavioural Safety Observations.
- [9] 32-418 Working at Heights Standard.
- [10]32-477 Safety, Health and Environment Training and Development Procedure.
- [11]32-520 Occupational Health and Safety Risk Assessment Procedure.
- [12]32-524 Developing a SHE Specification.
- [13]240-150642762 Plant Safety Regulations.
- [14]32-726 SHE requirements for Eskom Commercial Process.
- [15]32-727 Safety, Health, Environment and Quality Policy.
- [16] 240-114967625 Operating Regulations for High Voltage Systems.
- [17]240-61523882 LV Operating Regulations
- [18]32-1112 Disciplinary Code.
- [19]32-1113 Disciplinary Procedure.
- [20]240-44175132 Eskom Personal Protective Equipment Specification.
- [21]240-62946386 Vehicle and Driver Safety Management Procedure.
- [22]240-43848327 Right to Refuse Employees' Right of Refusal to Work in an Unsafe Situation Procedure.
- [23]240-84733329 Medical Surveillance Procedure.
- [24]240-100979499 Personal Protective Equipment for Working at Heights Specification.
- [25]240-78692652 Standard for use and maintenance of Earthing Gear
- [26] 240-69125290 Standard for the use of Equipotential Earth Footplate or MAT
- [27]240-146738795 Distribution High-voltage live working

Revision: 7

Page: 5 of 12

[28] 240-60725816 Transmission High-voltage live working

#### 2.2.2 Informative

[29] National Road Traffic Act 93 of 1996.[30] 240-58554227 Health and Safety Agreement

#### 2.3 Definitions

- **2.3.1 Contractor:** (Also referred to as mandatory as per section 1 of the OHS Act): Any employer formally contracted (directly or indirectly) by Eskom and who performs work and supplies a service, product, equipment or material to advance Eskom's business or other interests is classified as a contractor. This includes Eskom non-executive board members, personal contractors (that is, consultants) and third-party contractors (that is, vendors, suppliers, agents, joint ventures, principal contractors and subcontractors).
- **2.3.2 Equipotential zone:** means a safe work area created to ensure that any two or more conducting parts that can be touched by a person simultaneously are bonded together by approved earthing leads to ensure a zone of equal potential between different parts of the working area.
- **2.3.3 Life-Saving Rule:** Rules that, if not adhered to, have the potential to cause serious harm to people. The consequences of a person knowingly and wilfully violating this rule will result in a disciplinary process in accordance with the Eskom Disciplinary Code and Procedure.
- **2.3.4 Visitors:** Any person (including a minor) who visits an Eskom site/office during working hours to attend a meeting or for any reason whatsoever.
- 2.3.5 Work at height: This means any work performed above a stable work surface or where a person puts himself/herself in a position where he/she exposes himself/herself to a fall from or into. Work at height is, as a result, work in any place (except a staircase in a permanent workplace), including a place at, above or below ground level, where a person could be injured if he/she fell from that place. Access and egress that present a risk of fall can also be classified as work at height.
- **2.3.6 Zero Tolerance:** The standard that provides for the imposition of severe consequences for a prescribed offence or behaviour without making exceptions for extenuating circumstances.

Revision: 7

Page: 6 of 12

#### 2.4 Abbreviations

Abbreviation	Explanation
ISO	International Standard Organisation
OHS	Occupational Health and Safety
ORHVS	Operational Regulations for High Voltage Systems
PPE	Personal Protective Equipment
PSR	Plant Safety Regulations
PTW	Permit to Work
SHEQ	Safety, Health, Environment, and Quality
soc	State-Owned Company

## 2.5 Roles and responsibilities

# 2.5.1 Risk and Sustainability OHS Department

The Risk and Sustainability OHS Department shall:

- a) Compile and review the Life-Saving Rules for Occupational Health and Safety;
- b) Develop awareness material;
- c) Ensure that the rules are communicated throughout the business;
- d) Ensure compliance is monitored; and
- e) Ensure that violations that are related to safety incidents are communicated to the organisation.

## 2.5.2 All Groups/Divisions

The management at Group/Divisional/Subsidiaries level shall be responsible for:

- a) Implementing the Eskom Life-Saving Rules in their Groups/Divisions/Subsidiaries/Clusters/Business Units.
- b) Communicating to all their employees, contractors, contractor employees and visitors the importance of compliance with the Eskom Life-Saving Rules and the consequences of non-compliance therewith. This includes communicating Life-Saving Rules to all new employees and new contractors.
- c) Ensuring that the awareness material is made available, distributed and displayed at all workplaces.
- d) Ensuring all employees sign confirmation that the rules have been discussed with them, that they understand the rules and the consequences of violating these rules and retain copies thereof.
- e) Investigating any violation of a Life-Saving Rule and initiate the disciplinary process within five (5) working days.

Revision: 7

Page: 7 of 12

f) Ensuring consistency in the application of appropriate sanctions on employees, contractors and contractor employees.

# 2.5.3 All employees (Eskom and contractors)

- a) Always observe and adhere to the Life-Saving Rules.
- b) Ensure that you have the relevant training, competence and/or authorisation before undertaking any task.
- c) Avoid taking shortcuts when executing tasks. Always do the right thing even when no one is watching.
- d) Only perform work that you are authorised to do.
- e) Where the situation exists that there is a likelihood of a contravention of a Life-Saving Rule, you shall exercise the right to refuse to perform such work.

## 2.6 Process for monitoring

Groups/Divisions shall be responsible for ensuring compliance with the standard through their annual audit and inspection plans.

# 2.7 Related/Supporting documents

- [1] 240-62196227 Life-Saving Rules revision 6 (superseded).
- [2] 240–63942960 Life-Saving Rule Acknowledgement Form Document Content.

## 3. Document content

Life-Saving Rules are safety rules that, if not adhered to, have the potential to cause serious harm to people. The consequences of a person knowingly and wilfully violating these rules will result in a disciplinary process in accordance with the Eskom Disciplinary Code and Procedure.

The objective of this Standard is to clarify Eskom's intention to enforce "ZERO TOLERANCE" with respect to behaviour resulting in serious risk to an individual at the workplace.

It must be noted that the content of this standard does not detract from the requirements for safe behaviour for all other work-related activities or other health and safety requirements, but rather emphasises the importance thereof.

## 3.1 Eskom Life-Saving Rules

# 3.1.1 RULE 1: OPEN, ISOLATE, TEST, EARTH AND CREATE AN EQUIPOTENTIAL ZONE BEFORE TOUCH

To ensure a safe electrical work environment, no person may work/operate on, around or near any electrical network, line or apparatus, electrically connected to the power system and/or electrically charged and/or not electrically charged unless:

Life Saving-Rules Unique Identifier: 240-62196227

Revision: 7

Page: **8 of 12** 

a) He/she is trained and authorised as competent for the task to be done;

- b) There is a valid permit to work where required and they are being supervised by a competent person;
- c) A pre-task risk assessment to identify all risks and hazards has been conducted before any work commences;
- d) He/she follows the requirements on OPEN, ISOLATE, TEST, EARTH, AND CREATE AN EQUIPOTENTIAL ZONE BEFORE TOUCH, based on applicable/related standards, procedures and outcome of risk assessment fit for the type of work or task to be performed;
- e) The work area shall be within the equipotential zone, with the working earth visible at all times.
- f) The authorised person has physically shown all team members that the apparatus is safe to work on;
- g) He/she makes the specific electrical environment safe before performing the work; and
- h) All the appropriate PPE (including face shield and insulated gloves for ¹low voltage work) are worn

**Note:** The equipotential zone is only applicable for work being done on medium and high voltage apparatus.

## 3.1.2 RULE 2: HOOK UP AT HEIGHT

Working at height is a significant part of work in Eskom Holdings and is regarded as a high-risk activity, as a result, all precautions must be taken to prevent incidents while working at height.

Wherever reasonably practicable, preference must be given to the performance of work at ground level as opposed to work in an elevated position. Where work in an elevated position is necessary, the requirements in this document and all other Eskom requirements pertaining to working from height shall apply.

No person may work at height where there is a risk of falling unless:

- a) A Fall Protection Plan has been developed by a trained fall protection plan developer and communicated to all employees working at height based on the scope of work/task;
- b) He/she is medically fit to work at height;
- c) He/she is trained in accordance with Eskom's requirements for working at height
- d) A pre-task-specific work at height risk assessment to identify all risks and hazards has been conducted and communicated to all participants before commencing any work of this nature;
- e) He/she appropriately conducts work as determined by the risk assessment;
- f) He/she is appropriately secured during ascending and descending where applicable; and
- g) He/she is using an Eskom-approved fall arrest system where applicable.

Revision: 7

Page: 9 of 12

#### 3.1.3 RULE 3: BUCKLE UP

Where required, the proper wearing of seat belts for any driver, operator and passenger is mandatory in all vehicles/equipment when driving and/or travelling for Eskom business purposes. The driver is obligated to ensure that he/she as well as all passengers are properly seated and wearing their seatbelts at all times while being transported in the vehicle, as per Eskom specifications.

**Note:** This rule is applicable on any road or parking lot, irrespective of the speed, and when the vehicle moves in a forward or backward direction.

#### **3.1.4 RULE 4: BE SOBER**

No person who is under the influence or who appears to be under the influence of intoxicating liquor or drugs will be permitted to enter or remain on an Eskom site conduct Eskom business or drive/operate a vehicle/equipment for Eskom business purposes.

This includes any level of alcohol or the presence of any drugs, controlled substances, and/or illegal substances in the body that impairs or could impair mental and physical functioning, irrespective of when the substance was used.

## 3.1.5 RULE 5: ENSURE THAT YOU HAVE A PERMIT TO WORK

No person shall work without the required Permit to Work (PTW), which is governed by but not limited to:

- a) Plant Safety Regulations; or
- b) Operating Regulations for High Voltage Systems (ORHVS) (handover or permit); or
- c) Low Voltage Operating Regulations; or
- d) Any other activity where a permit is required, for example, driver and statutory permits.

No apparatus is to be returned to service without the cancellation of all permits on that plant in accordance with procedure, unless permission is granted for a particular plant to be returned to service with permits still open, like in the case of redundant systems.

**NOTE:** In the case of live work, a "Live Work Declaration Form" is to be completed by the authorised person, who is the person responsible for the safe execution of work according to relevant standards and procedures.

## 3.1.6 RULE 6: ENSURE SAFE LIVE WORKING

## To ensure safe live work, each live worker shall:

- a) Ensure all live work basic principles are adhered to, as outlined (for the method being used) in the High Voltage Live Working Standard for the respective division.
- b) Observe and maintain the minimum approach distance (MAD).
- c) Only perform live work (never mix live and dead work on the same site at the same time Refer to ORHVS Section 7 and 5 handouts respectively).

Revision: 7

Page: 10 of 12

d) Perform tasks they are authorised for and only undertake tasks that are documented in the respective Task Manual (TM). Only work on one potential (voltage) at a time.

# 3.2 Consequences of Violating a Life-Saving Rule

In terms of general health and safety in Eskom, if any of the Life-Saving Rules are violated, it will be treated as serious misconduct, and result in a disciplinary process in accordance with the Eskom Disciplinary Code and Procedure.

It must be highlighted that Eskom takes a ZERO TOLERANCE stance to violation of these rules.

Depending on the circumstances, Eskom reserves the right, where a contractor manager/supervisor allows the violation of a Life-Saving Rule, to suspend the contractor's activities while determining an appropriate sanction.

Where a contractor employee allegedly violates a Life-Saving Rule, the contractor shall immediately remove the employee from the site and initiate the disciplinary process. The contractor shall investigate any violation of a Life-Saving Rule and initiate the disciplinary process within five (5) working days of the violation. The contractor shall furnish Eskom with a copy of the sanction after the disciplinary process.

# 4. Acceptance

This document has been seen and accepted by:

Name	Designation		
Kerseri Pather	General Manager – Risk & Sustainability		
Miranda Moahlodi	Senior Manager – Risk & Sustainability – OHS		
Risk and Sustainability Management Committee	Members of the Risk and Sustainability Management Committee		
Centralised Consultative Forum	Members of the Centralised Consultative Forum		
HR Policies and Procedures Committee	Members of the Human Resources Policies and Procedures Committee		
OHS Steering Committee	Members of the OHS Steering Committee		

## 5. Revisions

Date	Rev.	Compiler	Remarks
February 2025	7	K Modiole	Document due for review and alignment to the organisational changes

Revision: 7

Page: **11 of 12** 

Date	Rev.	Compiler	Remarks
January 2017	6	A Stramrood	Substituted the words "Disciplinary hearing" with Disciplinary process.  Updated the Purpose and Applicability to specify that this Standard applies to contractors. Updated Normative and Informative References. Updated Definition section by removing agent and consultant as these have been incorporated into the definition of contractor. Updated the definition of Work at height and Zero Tolerance. Reviewed and updated the Roles and Responsibilities section and Process for monitoring. Added permit requirement to Rule 1, updated Rule 2 - Removed the words "psychologically fit to work" as this is no longer a requirement in terms of the Construction Regulations, 2014 and updated Rule 3 – Removed the words "(for example transporting people on the back of trucks in a cabin)" Updated Consequences of violating a Life-Saving Rule with regard to contractors.
October 2015	5	A Stramrood	The revision date needed to be extended. The content is still valid and the same.
May 2012	4	S Govender	Amended Section 3.6 Consequences of Violating a Life-Saving Rule to align with EXCO decision.
March 2013	3	S Govender	Changed Cardinal Rules to Life- Saving Rules and amended content to ensure a better understanding of the intent and requirements.
September 2010	2	K Terblanche	The content of Rev 1 was incorporated into the new policy template. The content was revised and updated.
December 2008	1	K Terblanche	Annexure 1: Acknowledgement of Eskom Life-saving Rules of this document was removed. The references made to Annexure 1 in paragraphs 3.5.2 and 3.8 were also removed.
August 2008	0	K Terblanche	The document with reference numbers 32-421 was developed and approved.

Revision: 7

Page: **12 of 12** 

## 6. Review Team

The following people were involved in the review of this document:

- Kgosi Modiole
- Sivi Govender
- Peter May
- Mike Townsend
- Sheryl Issacs
- Marc Lebea
- Mathula Thulare
- Jayson Naicker
- Nalini Ramnarian
- Bertie de Jager
- Loraine Smit
- Sifiso Ndlovu
- Silindokuhle Sithebe
- David Fankomo
- Petrus Motsumi
- Mike Voudouris (Distribution Live Work SME)
- Eric Marshall (NTCSA Live Work SME)
- Distribution Live Work Care Group
- Distribution Live Work Managers Forum
- Raj Rajkumar Transmission BIPM
- Andre van Heerden Distribution Training
- Francois Du Toit Officer Technical Support

# 7. Acknowledgements

None